

Overdetermined $2D$ Systems Invariant in One Direction and Their Transfer Functions

Andrey Melnikov, Victor Vinnikov

Ben-Gurion University of the Negev, Israel

December 19, 2008

Abstract

In this work we develop a theory of *Vessels*. This object arises [Li, V, BV] in the study of overdetermined $2D$ systems invariant in one of the variables, which are usually called *time invariant*. To each overdetermined time invariant $2D$ systems there is associated a vessel, which is a collection of system operators satisfying certain relations and vice versa. Such an invariance forces the theory of vessels to resemble a constant (classical) $1D$ case [NF, B, BC, BGR, BFKD] and as a result many notions are naturally redefined and most theorems are reproved in this setting. The notion of transfer function and its connection to the overdetermined $2D$ time invariant system (and the corresponding vessel) is one of the topics of this work. It is well known [BC, BFKD] that multiplicative structure of a transfer function of a $1D$ system is closely connected to the decomposition of the state space into invariant subspaces of the state operator and we generalize this result to a wider class of functions. This class (denoted by $\mathcal{I}$) arises as a class of transfer functions, which intertwine solutions of ODEs with spectral parameters [CoLe]. At the end we present solution of factorization problems for finite dimensional case.

Contents

1	Introduction	3
2	Overdetermined t_1 invariant $2D$ systems	4
2.1	$2D$ systems invariant in one direction	4
2.2	Overdeterminedness and compatibility	5
3	Vessel	9
3.1	Definition	9
3.2	Gauge quasi-similarity of vessels	10
3.3	Differential vessels	13
3.4	Separation of variables and the notion of transfer function	15
3.5	Class $\mathcal{I}$ of intertwining functions	17
4	Main theorem of gauge quasi similarity	18
5	Adjoint system	20

6	System and vessel operations	22
6.1	Cascade connection of systems	22
6.2	Inversion of systems	24
6.3	Projection, compression and cascade decomposition of systems	26
7	Kalman decomposition of Vessels	29
8	Analytic functions as transfer functions	31
8.1	Realization theorem for arbitrary analytic functions in $\mathcal{I}$	31
8.2	Realization theorem for matrix functions in $\mathcal{I}$	34
8.3	Realization theorem (of Mittag-Leffler type)	37

1 Introduction

The theory of two-dimensional ($2D$) overdetermined time-invariant systems has been extensively developed over the last 20 years; it is closely connected to the theory of commuting operators [LKMV], [BV], [V]. An overdetermined $2D$ continuous time-invariant linear i/s/o system is of the form

$$\Sigma : \begin{cases} \frac{\partial}{\partial t_1} x(t_1, t_2) = A_1 x(t_1, t_2) + B_1 u(t_1, t_2) \\ \frac{\partial}{\partial t_2} x(t_1, t_2) = A_2 x(t_1, t_2) + B_2 u(t_1, t_2) \\ y(t_1, t_2) = D u(t_1, t_2) + C x(t_1, t_2) \end{cases}$$

where $(u(t_1, t_2), x(t_1, t_2), y(t_1, t_2))$ is the (input, state, output) triple and all the other symbols denote bounded operator on suitable Hilbert spaces. Assuming continuously differentiable inputs, one obtains [BV] that the state space must be twice differentiable and enjoy the equality of mixed variables, from where algebraic relations are imposed on the operators of the system, and compatibility conditions (hence *overdetermined* system) on the input $u(t_1, t_2)$ and the output $y(t_1, t_2)$. More precisely, $u(t_1, t_2)$ and $y(t_1, t_2)$ satisfy algebraic equations (live on a curve) and an example of relation on the operators is commutativity of A_1, A_2 .

Using frequency domain analysis a notion of transfer function $S(\lambda, t_2)$ arises

$$S(\lambda) = D + C(\lambda I - A_1)^{-1} B_1$$

and the main question is how properties of such transfer functions and properties of the system operators (more precisely invariant subspaces of A_1, A_2) are connected. Many standard structural properties, e.g., controllability, observability, minimality, pairing and adjoint system, cascade connection, equivalence and standard problems, e.g., pole placement, linear-quadratic-regulator problem H^∞ control for $1D$ linear systems carry over for this setting.

The study of time varying $1D$ systems has produced a rich theory and the core of all these theories is the Sz.-Nagy–Foias theory of contractions on a Hilbert space [NF]. The analogue of transfer function in this setting is a lower block-triangular bounded operator. In [ABP], for example there is presented the development of a unified approach to time-varying dissipative linear systems, non-stationary Lax-Phillips scattering theory, and operator model theory for the infinite family of contractions. The abstract interpolation problem for the time-varying case is presented both in the de Branges-Rovnyak model formulation [dBR], and in its coordinate-free, scattering-theoretic form, and its application to the time-varying version of the matrix right tangential Nevanlinna-Pick problem is studied.

Probably, the simplest generalization of time varying $1D$ systems is the study of $2D$ systems invariant in one direction. There are some works in this direction [Li, Ga] in different settings. Our main inspiration comes from the article of M. Livšić [Li] and we actually continue this work.

So, we suppose that our $2D$ systems are invariant in one of the variables (t_1). We will use integrated form for of a system [La] and as a result there arises a continuous family of Hilbert spaces and semi-group acting between them. The invariance of the $2D$ system in one of the variables allows us to perform a partial separation of variables and to define a transfer function, depending on the corresponding spectral parameter (say λ), which will, additionally, depend on the second variable (t_2):

$$S(\lambda, t_2) = D(t_2) + C(t_2)(\lambda I - A_1(t_2))^{-1} B_1(t_2)$$

A fundamental feature in the study of transfer functions and their factorizations is that algebraic equations are now replaced by ODEs with a spectral parameter λ .

The theory of these systems is interesting by itself, especially since it allows us to use frequency domain analysis in a time varying framework. It also has important connections with completely integrable nonlinear PDEs [N]: the so-called Lax equation

$$\frac{d}{dt_2} A_1(t_2) = A_1(t_2)A_2(t_2) - A_2(t_2)A_1(t_2)$$

appears naturally, and the passage from the input to the output ODE with a spectral parameter is analogous to the Bäcklund transformation.

Let us introduce the detailed description of the contents of this work, highlighting the main results. Important notice is that we start the study of t_1 -invariant $2D$ systems from the more general integrated form, i.e., differential equations are presented as integral equations and as a result we obtain much weaker assumptions on the operators. Inspiration for doing it in this way comes from [La]. As always the case in this passage, we consider evolution semi groups acting between continuous set of Hilbert spaces. This semi-group, after appropriate transformation of the Hilbert spaces and differentiation gives rise to operator $A_2(t_2)$ in section 3.

There are seven sections in this work. After introduction, at the second section we introduce overdetermined $2D$ systems and show how basic notions of system theory carry over. Following the ideas in [V] we introduce two notions (local and global) of approximate controllability and similarly two notions for observability and study their relations. On this basis, we study in section 3 gauge quasi-similarity of (minimal) systems (vessels). One of the interesting results of our work is that there exists a notion of *differential vessel* and we show that it is always possible to pass from integral to differential form and vice versa. Further, we present the notion of transfer function and its main properties. As a result we define a class $\mathcal{I}$ of intertwining functions, which is extensively studied at the last section 8.

Next in section 4 we show that equivalence of transfer function for two vessels is equivalent to quasi-similarity between them. After that in section 5 the notion of adjoint system is presented. At section 6 we present basic operations on vessels: cascade connection, projection, compression, cascade decomposition. For the completeness of presentation we also discuss in section 7 Kalman decomposition in our setting that is very similar to the classical $1D$ case.

2 Overdetermined t_1 invariant $2D$ systems

2.1 $2D$ systems invariant in one direction

An overdetermined t_1 -invariant $2D$ system is a linear input-state-output (i/s/o) system, which consists of operators depending only on the variable t_2 ; in the most general case such a system is of the form [Li]

$$I\Sigma' : \begin{cases} x(t_1, t_2) = e^{A_1(t_2)(t_1 - t_1^0)} x(t_1^0, t_2) + \int_{t_1^0}^{t_1} e^{A_1(t_2)(t_1 - y)} B_1(t_2) u(y, t_2) dy \\ x(t_1, t_2) = F(t_2, t_2^0) x(t_1, t_2^0) + \int_{t_2^0}^{t_2} F(t_2, s) B_2(s) u(t_1, s) ds \\ y(t_1, t_2) = C(t_2) x(t_1, t_2) + D(t_2) u(t_1, t_2) \end{cases}$$

where for Hilbert spaces $\mathcal{E}, \mathcal{E}_*, \mathcal{H}_{t_2}$ there are defined

$$\begin{aligned} u(t_1, t_2) &\in \mathcal{E} - \text{input}, \\ y(t_1, t_2) &\in \mathcal{E}_* - \text{output}, \\ x(t_1, t_2) &\in \mathcal{H}_{t_2} - \text{state}, \end{aligned}$$

such that $u(t_1, t_2), y(t_1, t_2)$ are absolutely continuous functions of each variable when the other variable is fixed. The transition of the system will usually be considered from (t_1^0, t_2^0) to (t_1, t_2) . Note that $\mathcal{H}_{t_2}$ are a priori different for each t_2 , and as a result $F(t_2, t_2^0)$ has to be an evolution semi-group, i.e., it satisfies the following definition

Definition 2.1 *Given a collection of Hilbert spaces $\{\mathcal{H}_t \mid t \in I\}$ for an interval $I \subseteq \mathbb{R}$ and a collection of bounded invertible operators $F(s, t) : \mathcal{H}_s \rightarrow \mathcal{H}_t$ for each $s, t \in I$, we will say that $F(s, t)$ is **evolution semi-group** if the following relations hold for all $r, t, s \in I$:*

$$\begin{aligned} F(r, s)F(s, t) &= F(r, t), \\ F(t, t) &= Id|_{\mathcal{H}_t}. \end{aligned}$$

In order to be sure that all the formulas are meaningful we shall make the following regularity assumptions

Assumption 2.2 *Internal regularity:*

1. $A_1(t_2) : \mathcal{H}_{t_2} \rightarrow \mathcal{H}_{t_2}, B_1(t_2), B_2(t_2) : \mathcal{E} \rightarrow \mathcal{H}_{t_2}, C(t_2) : \mathcal{H}_{t_2} \rightarrow \mathcal{E}_*$ are bounded operators (for all t_2) and $F(t_2, t_2^0) : \mathcal{H}_{t_2^0} \rightarrow \mathcal{H}_{t_2}$ is an evolution semi-group (see definition 2.1).
2. $F(t_2, s)B_2(s)$ and $C(s)F(s, t_2)$ are absolutely continuous as functions of s (for almost all t_2) in the norm operator topology on $\mathcal{L}(\mathcal{E}, \mathcal{H}_{t_2})$ and on $\mathcal{L}(\mathcal{E}_*, \mathcal{H}_{t_2})$, respectively.

Assumption 2.3 *Feed through regularity:* the operator $D(t_2) : \mathcal{E} \rightarrow \mathcal{E}_*$ is an absolutely continuous function of t_2 .

Since our entries $u(t_1, t_2)$ will be locally integrable as functions of t_1 , and as a result the first equation may be equivalently considered in the differential form, we shall work with systems of the following form:

$$I\Sigma : \begin{cases} \frac{\partial}{\partial t_1} x(t_1, t_2) = A_1(t_2)x(t_1, t_2) + B_1(t_2)u(t_1, t_2) \\ x(t_1, t_2) = F(t_2, t_2^0)x(t_1, t_2^0) + \int_{t_2^0}^{t_2} F(t_2, s)B_2(s)u(t_1, s)ds \\ y(t_1, t_2) = C(t_2)x(t_1, t_2) + D(t_2)u(t_1, t_2) \end{cases} \quad (2.1)$$

2.2 Overdeterminedness and compatibility

To ensure that the overdetermined systems equations (2.1) are compatible, we shall demand the equality of the two transitions for our system:

1. $(t_1^0, t_2^0) \longrightarrow (t_1^0, t_2) \longrightarrow (t_1, t_2),$
2. $(t_1^0, t_2^0) \longrightarrow (t_1, t_2^0) \longrightarrow (t_1, t_2).$

for arbitrary $(t_1^0, t_2^0), (t_1, t_2)$. In the first case

$$\begin{aligned} x(t_1, t_2) = & e^{A_1(t_2)(t_1-t_1^0)} F(t_2, t_2^0) x(t_1^0, t_2^0) + \\ & + e^{A_1(t_2)(t_1-t_1^0)} \int_{t_2^0}^{t_2} F(t_2, s) B_2(s) u(t_1^0, s) ds + \\ & + \int_{t_1^0}^{t_1} e^{A_1(t_2)(t_1-p)} B_1(t_2) u(p, t_2) dp \end{aligned}$$

and in the second:

$$\begin{aligned} \tilde{x}(t_1, t_2) = & F(t_2, t_2^0) e^{A_1(t_2^0)(t_1-t_1^0)} x(t_1^0, t_2^0) + \\ & + F(t_2, t_2^0) \int_{t_1^0}^{t_1} e^{A_1(t_2^0)(t_1-p)} B_1(t_2^0) u(p, t_2^0) dp + \\ & + \int_{t_2^0}^{t_2} F(t_2, s) B_2(s) u(t_1, s) ds. \end{aligned}$$

The compatibility condition for free evolution ($u \equiv 0$) results in

$$e^{A_1(t_2)(t_1-t_1^0)} F(t_2, t_2^0) x(t_1^0, t_2^0) = F(t_2, t_2^0) e^{A_1(t_2^0)(t_1-t_1^0)} x(t_1^0, t_2^0)$$

or

$$A_1(t_2) = F(t_2, t_2^0) A_1(t_2^0) F(t_2^0, t_2) \quad (2.2.Lax)$$

which is called the Lax equation [N] and plays an important role in the theory of completely integrable non-linear PDEs. Note that it follows that the spectrum of $A_1(t_2)$ is independent of t_2 .

Inserting the Lax condition into $x(t_1, t_2) = \tilde{x}(t_1, t_2)$ and rearranging the summands we obtain:

$$\begin{aligned} e^{A_1(t_2)(t_1-t_1^0)} \int_{t_2^0}^{t_2} F(t_2, s) B_2(s) u(t_1^0, s) ds - \int_{t_2^0}^{t_2} F(t_2, s) B_2(s) u(t_1, s) ds = \\ = F(t_2, t_2^0) \int_{t_1^0}^{t_1} e^{A_1(t_2^0)(t_1-p)} B_1(t_2^0) u(p, t_2^0) dp - \int_{t_1^0}^{t_1} e^{A_1(t_2)(t_1-p)} B_1(t_2) u(p, t_2) dp \end{aligned}$$

Multiplying this equality on the left by $e^{-A_1(t_2)t_1}$ we reach

$$\begin{aligned} e^{-A_1(t_2)t_1^0} \int_{t_2^0}^{t_2} F(t_2, s) B_2(s) u(t_1^0, s) ds - e^{-A_1(t_2)t_1} \int_{t_2^0}^{t_2} F(t_2, s) B_2(s) u(t_1, s) ds = \\ = e^{-A_1(t_2)t_1} F(t_2, t_2^0) \int_{t_1^0}^{t_1} e^{A_1(t_2^0)(t_1-p)} B_1(t_2^0) u(p, t_2^0) dp - \int_{t_1^0}^{t_1} e^{-A_1(t_2)p} B_1(t_2) u(p, t_2) dp \end{aligned}$$

Since $u(p, s)$, $e^{-A_1(t_2)p}$ are absolutely continuous functions in each variable, we can rewrite it as an equality of iterated integrals of the derivatives (which are locally absolutely integrable as functions of one variable):

$$\int_{t_2^0}^{t_2} \int_{t_1^0}^{t_1} \frac{d}{dp} [e^{-A_1(t_2)p} F(t_2, s) B_2(s) u(p, s)] dp ds = \int_{t_1^0}^{t_1} \int_{t_2^0}^{t_2} \frac{d}{ds} [e^{-A_1(t_2)p} F(t_2, s) B_1(s) u(p, s)] ds dp.$$

Notice that this integral equality is correct for all t_1^0, t_2^0, t_1, t_2 . Moreover, the functions $e^{-A_1(t_2)p} F(t_2, s) B_2(s) u(p, s)$ and $e^{-A_1(t_2)p} F(t_2, s) B_1(s) u(p, s)$ are absolutely continuous and as a result their derivatives are integrable functions, meaning that these two integrals are actually equal by Fubini's theorem to a two-dimensional integral over the rectangle $\{(p, s) \mid t_1^0 \leq p \leq t_1, t_2^0 \leq s \leq t_2\}$. Thus it is equivalent to

$$\frac{d}{dp} [e^{-A_1(t_2)p} F(t_2, s) B_2(s) u(p, s)] = \frac{d}{ds} [e^{-A_1(t_2)p} F(t_2, s) B_1(s) u(p, s)]$$

for almost all (p, s) . This in turn is simply the following equation

$$\begin{aligned} -A_1(t_2) e^{-A_1(t_2)p} F(t_2, s) B_2(s) u(p, s) + e^{-A_1(t_2)p} F(t_2, s) B_2(s) \frac{\partial}{\partial p} u(p, s) = \\ e^{-A_1(t_2)p} \frac{\partial}{\partial s} [F(t_2, s) B_1(s)] u(p, s) + e^{-A_1(t_2)p} F(t_2, s) B_1(s) \frac{\partial}{\partial s} u(p, s). \end{aligned}$$

Using (2.2.Lax) again we shall obtain

$$\begin{aligned} -F(t_2, s) A_1(s) B_2(s) u(p, s) + F(t_2, s) B_2(s) \frac{\partial}{\partial p} u(p, s) = \\ = \frac{\partial}{\partial s} [F(t_2, s) B_1(s)] u(p, s) + F(t_2, s) B_1(s) \frac{\partial}{\partial s} u(p, s), \end{aligned}$$

or, after multiplying on the left by $F(s, t_2)$ and then substituting back the variables $(p, s, t_2) \rightarrow (t_1, t_2, t_2^0)$

$$B_2(t_2) \frac{\partial}{\partial t_1} u(t_1, t_2) - B_1(t_2) \frac{\partial}{\partial t_2} u(t_1, t_2) - (A_1(t_2) B_2(t_2) + F(t_2, t_2^0) \frac{\partial}{\partial t_2} [F(t_2^0, t_2) B_1(t_2)]) u(t_1, t_2) = 0. \quad (2.3)$$

At this stage it is convenient to assume that we have factorization

$$\begin{aligned} B_2(t_2) &= \tilde{B}(t_2) \sigma_2(t_2), \quad B_1(t_2) = \tilde{B}(t_2) \sigma_1(t_2), \\ A_1(t_2) B_2(t_2) + F(t_2, t_2^0) \frac{\partial}{\partial s} [F(t_2^0, t_2) B_1(t_2)] &= -\tilde{B}(t_2) \gamma(t_2) \end{aligned} \quad (2.4)$$

for some operators

$$\tilde{B}(t_2) : \tilde{\mathcal{E}} \rightarrow \mathcal{H}_{t_2}, \quad \sigma_2(t_2), \sigma_1(t_2), \gamma(t_2) : \mathcal{E} \rightarrow \tilde{\mathcal{E}},$$

where $\tilde{\mathcal{E}}$ is another auxiliary Hilbert space. It is also important to postulate the following assumption in order to give meaning to the corresponding formulas:

Assumption 2.4 *External input regularity:*

1. $\gamma(t_2), \sigma_2(t_2) \in L_{loc}^1(\mathcal{L}(\mathcal{E}, \tilde{\mathcal{E}}))$ in the norm operator topology.
2. $\sigma_1(t_2) \in L(\mathcal{E}, \tilde{\mathcal{E}})$ is absolutely continuous and invertible, in the norm operator topology.

Expressed directly in terms of the operators $\tilde{B}(t_2), \sigma_1(t_2), \sigma_2(t_2)$ with $B_1(t_2), B_2(t_2)$ eliminated, (2.4) becomes

$$\frac{d}{dt_2}(F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1(t_2)) + F(t_2^0, t_2)A_1(t_2)\tilde{B}(t_2)\sigma_2(t_2) + F(t_2^0, t_2)\tilde{B}(t_2)\gamma(t_2) = 0. \quad (2.5.OverD)$$

Then the condition (2.3) becomes

$$\tilde{B}(t_2)[\sigma_2(t_2)\frac{\partial}{\partial t_1}u(t_1, t_2) - \sigma_1(t_2)\frac{\partial}{\partial t_2}u(t_1, t_2) + \gamma(t_2)]u(t_1, t_2) = 0.$$

A sufficient condition for this to hold (which is necessary in case $\tilde{B}(t_2)$ is injective) is the *input compatibility condition*

$$\sigma_2(t_2)\frac{\partial}{\partial t_1}u(t_1, t_2) - \sigma_1(t_2)\frac{\partial}{\partial t_2}u(t_1, t_2) + \gamma(t_2)u(t_1, t_2) = 0 \quad (2.6)$$

Note that since $u(t_1, t_2)$ is the solution of PDE in the extended sense, it will be absolutely continuous as a function of t_1 for almost all t_2 , and conversely, it will be absolutely continuous as a function of t_2 for almost all t_1 .

The output $y(t_1, t_2)$ should satisfy the *output compatibility condition* of the same type as for the input compatibility condition (2.6), namely:

$$\sigma_{2*}(t_2)\frac{\partial}{\partial t_1}y(t_1, t_2) - \sigma_{1*}(t_2)\frac{\partial}{\partial t_2}y(t_1, t_2) + \gamma_*(t_2)y(t_1, t_2) = 0. \quad (2.7)$$

where similarly we have the following assumptions using an auxiliary output space $\tilde{\mathcal{E}}_*$

Assumption 2.5 *External output regularity:*

1. $\gamma_*(t_2), \sigma_{2*}(t_2) \in L_{loc}^1(\mathcal{L}(\mathcal{E}_*, \tilde{\mathcal{E}}_*))$ in the norm operator topology.
2. $\sigma_{1*}(t_2) \in L(\mathcal{E}_*, \tilde{\mathcal{E}}_*)$ is absolutely continuous and invertible, in the norm operator topology.

So, inserting here $y(t_1, t_2) = D(t_2)u(t_1, t_2) + C(t_2)x(t_2, t_2)$ we obtain that

$$\begin{aligned} 0 &= [\sigma_{2*}(t_2)\frac{\partial}{\partial t_1} - \sigma_{1*}(t_2)\frac{\partial}{\partial t_2} + \gamma_*(t_2)]y(t_1, t_2) = \\ &= [\sigma_{2*}(t_2)\frac{\partial}{\partial t_1} - \sigma_{1*}(t_2)\frac{\partial}{\partial t_2} + \gamma_*(t_2)][D(t_2)u(t_1, t_2) + C(t_2)x(t_2, t_2)] \\ &= \sigma_{2*}(t_2)C(t_2)\frac{\partial}{\partial t_1}x(t_2, t_2) - \sigma_{1*}(t_2)\frac{\partial}{\partial t_2}[C(t_2)x(t_2, t_2)] + \gamma_*(t_2)C(t_2)x(t_2, t_2) + \\ &\quad + \sigma_{2*}(t_2)D(t_2)\frac{\partial}{\partial t_1}u(t_2, t_2) - \sigma_{1*}(t_2)\frac{\partial}{\partial t_2}[D(t_2)u(t_2, t_2)] + \gamma_*(t_2)D(t_2)u(t_2, t_2). \end{aligned}$$

Substituting here the first system equation from (2.1), we obtain (after omitting the notation of dependence on the variables)

$$\begin{aligned} 0 &= \sigma_{2*}C(A_1x + \tilde{B}\sigma_1u) - \sigma_{1*}\frac{\partial}{\partial t_2}[Cx] + \gamma_*Cx + \sigma_{2*}D\frac{\partial}{\partial t_1}u - \sigma_{1*}[D'u + D\frac{\partial}{\partial t_2}u] + \gamma_*Du = \\ &= \sigma_{2*}CA_1x - \sigma_{1*}\frac{\partial}{\partial t_2}[Cx] + \gamma_*Cx + \\ &\quad + [\sigma_{2*}D\frac{\partial}{\partial t_1} - \sigma_{1*}D\frac{\partial}{\partial t_2} + \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}D' + \gamma_*D]u. \end{aligned}$$

Multiplying the second equation of the system (2.1) by $C(t_2)$ and differentiating with respect to t_2 , one can easily obtain that $\frac{\partial}{\partial t_2}[Cx]$ satisfies:

$$\frac{\partial}{\partial t_2}[Cx] = \frac{\partial}{\partial t_2}[CF]F^{-1}x + C\tilde{B}\sigma_2u.$$

Inserting this into the last equation we obtain

$$\begin{aligned} 0 &= \sigma_{2*}CA_1x - \sigma_{1*}[\frac{\partial}{\partial t_2}[CF]F^{-1}x + C\tilde{B}\sigma_2u] + \gamma_*Cx + \\ &\quad + [\sigma_{2*}D\frac{\partial}{\partial t_1} - \sigma_{1*}D\frac{\partial}{\partial t_2} + \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}D' + \gamma_*D]u = \\ &= [\sigma_{2*}CA_1 - \sigma_{1*}\frac{\partial}{\partial t_2}[CF]F^{-1} + \gamma_*C]x + \\ &\quad + [\sigma_{2*}D\frac{\partial}{\partial t_1} - \sigma_{1*}D\frac{\partial}{\partial t_2} + \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}C\tilde{B}\sigma_2 + \sigma_{1*}D' + \gamma_*D]u. \end{aligned} \tag{2.8}$$

The validity of this equation for the special case $u(t_1, t_2) = 0$ and an arbitrary initial $x(t_1^0, t_2^0)$ forces us to impose

$$0 = \sigma_{2*}CA_1F - \sigma_{1*}\frac{\partial}{\partial t_2}[CF] + \gamma_*CF. \tag{2.9.OverD}$$

With (2.9.OverD) in force, (2.8) collapses to

$$0 = [\sigma_{2*}D\frac{\partial}{\partial t_1} - \sigma_{1*}D\frac{\partial}{\partial t_2} + \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}C\tilde{B}\sigma_2 + \sigma_{1*}D' + \gamma_*D]u.$$

On the other hand, u satisfies the input compatibility condition (2.6), so it is natural to assume that there is an operator $\tilde{D} : \mathcal{E}_* \rightarrow \tilde{\mathcal{E}}_*$ satisfying

Assumption 2.6 *External feed through regularity: the operator $\tilde{D}(t_2) : \mathcal{E}_* \rightarrow \tilde{\mathcal{E}}_*$ is an absolutely continuous function of t_2 ,*

and which satisfies the following intertwining conditions, which will be called from now on the *linkage conditions*

$$\begin{aligned} \sigma_{1*}D &= \tilde{D}\sigma_1, & \sigma_{2*}D &= \tilde{D}\sigma_2, \\ \tilde{D}\gamma &= \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}C\tilde{B}\sigma_2 + \sigma_{1*}D' + \gamma_*D. \end{aligned} \tag{2.10.Link}$$

3 Vessel

3.1 Definition

Let us combine together all the formulas we have just developed. We define an (integral) **vessel** to be a collection of operator and spaces

$$\mathfrak{V} = (A_1(t_2), F(t_2, t_2^0), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{H}_{t_2}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

satisfying regularity assumptions 2.2, 2.3, 2.4, 2.5, 2.6 and the following vessel conditions:

$$F(t_2, t_2^0)A_1(t_2^0) = A_1(t_2)F(t_2, t_2^0) \quad (2.2.\text{Lax})$$

$$\frac{d}{dt_2}(F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1(t_2)) + F(t_2^0, t_2)A_1(t_2)\tilde{B}(t_2)\sigma_2(t_2) + F(t_2^0, t_2)\tilde{B}(t_2)\gamma(t_2) = 0 \quad (2.5.\text{OverD})$$

$$\sigma_{2*}(t_2)C(t_2)A_1(t_2)F(t_2, t_2^0) - \sigma_{1*}(t_2)\frac{d}{dt_2}[C(t_2)F(t_2, t_2^0)] + \gamma_*(t_2)C(t_2)F(t_2, t_2^0) = 0 \quad (2.9.\text{OverD})$$

$$\begin{aligned} \sigma_{1*}D &= \tilde{D}\sigma_1, & \sigma_{2*}D &= \tilde{D}\sigma_2, \\ \tilde{D}\gamma &= \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}C\tilde{B}\sigma_2 + \sigma_{1*}D' + \gamma_*D. \end{aligned} \quad (2.10.\text{Link})$$

It is naturally associated to the system $I\Sigma$ (see (2.1))

$$I\Sigma : \begin{cases} \frac{\partial}{\partial t_1}x(t_1, t_2) = A_1(t_2)x(t_1, t_2) + \tilde{B}(t_2)\sigma_1(t_2)u(t_1, t_2) \\ x(t_1, t_2) = F(t_2, t_2^0)x(t_1, t_2^0) + \int_{t_2^0}^{t_2} F(t_2, s)\tilde{B}(s)\sigma_2(s)u(t_1, s)ds \\ y(t_1, t_2) = C(t_2)x(t_1, t_2) + D(t_2)u(t_1, t_2). \end{cases} \quad (3.1)$$

with absolutely continuous inputs and outputs, satisfying compatibility conditions (2.6), (2.7) for almost all (t_1, t_2) :

$$\begin{aligned} \sigma_2(t_2)\frac{\partial}{\partial t_1}u(t_1, t_2) - \sigma_1(t_2)\frac{\partial}{\partial t_2}u(t_1, t_2) + \gamma(t_2)u(t_1, t_2) &= 0, \\ \sigma_{2*}(t_2)\frac{\partial}{\partial t_1}y(t_1, t_2) - \sigma_{1*}(t_2)\frac{\partial}{\partial t_2}y(t_1, t_2) + \gamma_*(t_2)y(t_1, t_2) &= 0. \end{aligned}$$

We shall further name these conditions as follows. (2.2.Lax) is the *Lax equation*. (2.5.OverD) and (2.9.OverD) are the *input and the output vessel conditions*, respectively. (2.10.Link) is the *linkage condition*.

3.2 Gauge quasi-similarity of vessels

As in the classical case, in order to deal with some classification of systems (to be defined later) we need a notion of minimal systems. In the $1D$ case there is only one natural notion of approximate controllability and observability. In the case of $2D$ t_1 invariant systems, on the other hand, there are at least the following two notions

Definition 3.1 *System $I\Sigma$ (3.1) is called **locally approximately controllable at t_2** if*

$$\mathcal{C}_{t_2} = \{h \in \mathcal{H}_{t_2} \mid \exists t_1 \in \mathbb{R}, (u, x, y) \in \mathcal{T} : x(0, t_2) = 0, x(t_1, t_2) = h\}$$

is dense in $\mathcal{H}_{t_2}$.

Here $\mathcal{T}$ stands for the set of system trajectories (u, x, y) of (3.1) with compatibility ODEs 3.7) and (3.8) with the spectral parameter λ .

Definition 3.2 *System $I\Sigma$ (3.1) is called **approximately controllable at t_2** if*

$$\tilde{\mathcal{C}}_{t_2} = \{h \in \mathcal{H}_{t_2} \mid \exists t_1 \in \mathbb{R}, (u, x, y) \in \mathcal{T} : x(0, 0) = 0, x(t_1, t_2) = h\}$$

is dense in $\mathcal{H}_{t_2}$.

Similarly to the classical case one immediately obtains that

$$\begin{aligned}\mathcal{C}_{t_2} &= \overline{\text{span}}\{\text{Im } A_1^j(t_2)B(t_2) \mid j = 0, 1, 2, \dots\}, \\ \tilde{\mathcal{C}}_{t_2} &= \overline{\text{span}}\{\text{Im } F(t_2, s)A_1^j(s)B(s) \mid j = 0, 1, 2, \dots, s \in \mathbb{R}\}.\end{aligned}$$

Notice that $F(t_2, t'_2)\tilde{\mathcal{C}}_{t'_2} = \tilde{\mathcal{C}}_{t_2}$ and since $F(t_2, t'_2)$ are bounded invertible operators, the density of $\tilde{\mathcal{C}}_{t_2}$ for any value of t_2 implies density for all t_2 , which means that the notion of approximate controllability is independent of t_2 .

Since $F(t_2, t_2) = Id$, we obtain that $\mathcal{C}_{t_2} \subseteq \tilde{\mathcal{C}}_{t_2}$ for all t_2 and consequently, if $\mathcal{C}_{t_2}$ is dense in $\mathcal{H}_{t_2}$ then so is $\tilde{\mathcal{C}}_{t_2}$. But actually the converse also holds

Theorem 3.1 *For the system $I\Sigma$ (3.1), satisfying regularity assumptions 2.2, 2.3, 2.4, 2.5, 2.6 the local approximate controllability for arbitrary t_2^0 is equivalent to approximate controllability for all t_2 .*

Proof: We have seen that

$$\mathcal{C}_{t_2^0} = \mathcal{H}_{t_2^0} \Rightarrow \tilde{\mathcal{C}}_{t_2^0} = \mathcal{H}_{t_2^0} \Rightarrow \tilde{\mathcal{C}}_{t_2} = \mathcal{H}_{t_2}$$

and we need to prove the converse. Suppose that for a fixed t_2^0 we have approximate controllability, which means that

$$\bigvee_{n \geq 0, e \in \mathcal{E}} F(t_2^0, s)A_1^n(s)B(s)e = \mathcal{H}_{t_2^0}$$

or what is equivalent

$$B^*(s)F^*(t_2^0, s)A_1^*(t_2^0)h = 0, \quad \forall h \in \mathcal{H}_{t_2^0}.$$

In the same manner local approximate controllability means that

$$\bigvee_{n \geq 0, e \in \mathcal{E}} A_1^n(t_2^0)B(t_2^0)e = \mathcal{H}_{t_2^0} \Rightarrow B^*(t_2^0)A_1^{*n}(t_2^0)h = 0, \quad \forall h \in \mathcal{H}_{t_2^0}.$$

Consider now a function with values in $\mathcal{E}$ for each $h \in \mathcal{H}_{t_2^0}$

$$u_h(\lambda, t_2, t_2^0) = B^*(t_2)F^*(t_2^0, t_2)(\lambda I - A_1^*(t_2^0))^{-1}h, \quad u_h(\lambda, t_2^0, t_2^0) = B^*(t_2^0)(\lambda I - A_1^*(t_2^0))^{-1}h$$

which is analytic at the neighborhood of $\lambda = \infty$. This function satisfies the following differential equation (adjoint of the input vessel condition (2.5.OverD))

$$\begin{aligned}\frac{d}{dt_2}u_h(\lambda, t_2, t_2^0) &= \frac{d}{dt_2}[B^*(t_2)F^*(t_2^0, t_2)(\lambda I - A_1^*(t_2^0))^{-1}h] = \\ &= \sigma_1^{-1}[-\sigma_2 B^*(t_2)F^*(t_2^0, t_2)A_1^{*n}(t_2^0)(\lambda I - A_1^*(t_2^0))^{-1}h + \gamma B^*(t_2)F^*(t_2^0, t_2)A_1^{*n}(t_2^0)(\lambda I - A_1^*(t_2^0))^{-1}h] = \\ &= \sigma_1^{-1}[-\sigma_2 B^*(t_2)F^*(t_2^0, t_2)(A_1^{*n}(t_2^0) - \lambda I + \lambda I)(\lambda I - A_1^*(t_2^0))^{-1}h + \gamma u_h(\lambda, t_2, t_2^0)] = \\ &= \sigma_1^{-1}[-\sigma_2 \lambda + \gamma]u_h(\lambda, t_2, t_2^0) + \sigma_1^{-1}\sigma_2 B^*(t_2)F^*(t_2^0, t_2)h.\end{aligned}$$

denoting by $\Phi(\lambda, t_2, t_2^0)$ the fundamental solution of the differential equation

$$\frac{d}{dt_2}\Phi(\lambda, t_2, t_2^0) = \sigma_1^{-1}[-\sigma_2 \lambda + \gamma]\Phi(\lambda, t_2, t_2^0)$$

and using variation of parameters, we shall obtain that

$$\begin{aligned}u_h(\lambda, t_2, t_2^0) &= \Phi(\lambda, t_2, t_2^0)\left[\int_{t_2^0}^{t_2}\Phi^{-1}(\lambda, y, t_2^0)\sigma_1^{-1}\sigma_2 B^*(y)F^*(t_2^0, y)h + u_h(\lambda, t_2^0, t_2^0)\right] = \\ &= \Phi(\lambda, t_2, t_2^0)\left[\int_{t_2^0}^{t_2}\Phi^{-1}(\lambda, y, t_2^0)\sigma_1^{-1}\sigma_2 B^*(y)F^*(t_2^0, y)h + B^*(t_2^0)(\lambda I - A_1^*(t_2^0))^{-1}h\right] = \\ &= \Phi(\lambda, t_2, t_2^0)\int_{t_2^0}^{t_2}\Phi^{-1}(\lambda, y, t_2^0)\sigma_1^{-1}\sigma_2 B^*(y)F^*(t_2^0, y)h + \Phi(\lambda, t_2, t_2^0)B^*(t_2^0)(\lambda I - A_1^*(t_2^0))^{-1}h,\end{aligned}$$

which is a sum of an analytic (in λ) $\mathcal{E}$ -valued function and of a function with poles (for λ in the spectrum of $A_1^*(t_2^0)$)

$$\Phi(\lambda, t_2, t_2^0)B^*(t_2^0)(\lambda I - A_1^*(t_2^0))^{-1}h.$$

So, if there is a vector $h \in \mathcal{H}_{t_2^0}$ such that $u_h(\lambda, t_2, t_2^0) = 0$ for each value of λ , it has to vanish the part containing the pole first. This means that for all λ out of the spectrum of $A_1^*(t_2^0)$

$$\Phi(\lambda, t_2, t_2^0)B^*(t_2^0)(\lambda I - A_1^*(t_2^0))^{-1}h = 0$$

and since $\Phi(\lambda, t_2, t_2^0)$ is invertible we obtain,

$$B^*(t_2^0)A_1^{*n}(t_2^0)h = 0,$$

which is local approximate controllability. □

The following notions are natural generalizations of the 1D case:

Definition 3.3 *The system $I\Sigma$ is **locally observable at t_2** if*

$$\mathcal{O}_{t_2}^\perp = \{h \in \mathcal{H}_{t_2} \mid x(0, t_2) = h, (u, x, y) \in \mathcal{T}, u(t_1, t_2) = 0 \Rightarrow y(t_1, t_2) = 0 \text{ for all } t_1\} = \{0\},$$

*and the system is **observable at t_2** if*

$$\tilde{\mathcal{O}}_{t_2}^\perp = \{h \in \mathcal{H} \mid x(0, 0) = h, (u, x, y) \in \mathcal{T}, u = 0 \Rightarrow y = 0 \text{ for all } t_1\} = \{0\}.$$

Again, similarly to the classical case one obtains that

$$\begin{aligned} \mathcal{O}_{t_2}^\perp &= \bigcap_{n \in \mathbb{N}} \text{Ker } C(t_2)A_1^n(t_2), \\ \tilde{\mathcal{O}}_{t_2}^\perp &= \bigcap_{n \in \mathbb{N}, s \in \mathbb{R}} \text{Ker } C(s)A_1^n(s)F(s, t_2). \end{aligned}$$

From the property of the evolution semi-group $F(t_2, t_2) = I$ we obtain that $\mathcal{O}_{t_2}^\perp \supseteq \tilde{\mathcal{O}}_{t_2}^\perp$ and that local observability at t_2 (i.e., $\mathcal{O}_{t_2}^\perp = \{0\}$) implies observability at t_2 (i.e., $\tilde{\mathcal{O}}_{t_2}^\perp = \{0\}$). Additionally, $\tilde{\mathcal{O}}_{t_2}^\perp = \tilde{\mathcal{O}}_{t_2'}^\perp F(t_2', t_2)$ implies that observability is independent of t_2 , i.e., if for any t_2^0 , $\tilde{\mathcal{O}}_{t_2^0}^\perp = \{0\}$ then $\tilde{\mathcal{O}}_{t_2}^\perp = \{0\}$ for all t_2 . Finally, a parallel to the controllability theorem.

Theorem 3.2 *For the system $I\Sigma$ (3.1), satisfying regularity assumptions 2.2, 2.3, 2.4, 2.5, 2.6 the local observability for arbitrary t_2^0 is equivalent to observability for all t_2 .*

Proof: We have seen that

$$\mathcal{O}_{t_2^0}^\perp = \{0\} \Rightarrow \tilde{\mathcal{O}}_{t_2^0}^\perp = \{0\} \Rightarrow \tilde{\mathcal{O}}_{t_2}^\perp = \{0\}$$

and it is remained to show the converse. Similarly to the proof of local approximate controllability for each t_2 , supposing observability at a fixed t_2

$$\tilde{\mathcal{O}}_{t_2}^\perp = \bigcap_{n \in \mathbb{N}, s \in \mathbb{R}} \text{Ker } C(s)A_1^n(s)F(s, t_2) = \{0\},$$

we may consider a function of λ with values in $\mathcal{E}$

$$y_h(\lambda, t_2, t_2^0) = C(t_2)F(t_2, t_2^0)(\lambda I - A_1(t_2^0))^{-1}h,$$

and the output vessel condition (2.9.OverD)

$$\sigma_{2*}(t_2)y_{A_1(t_2^0)h}(t_2) - \sigma_{1*}(t_2)\frac{d}{dt_2}y_h(t_2) + \gamma_*(t_2)y_h(t_2) = 0, \quad y_h(\lambda, t_2^0, t_2^0) = C(t_2^0)(\lambda I - A_1(t_2^0))^{-1}h$$

and follow the same lines as in the proof of local approximate controllability. $\square$

The system $I\Sigma$ is called *minimal* if it is both approximately controllable and observable, i.e., $(\mathcal{C}_{t_2} = \mathcal{O}_{t_2} = \mathcal{H})$.

A natural notion of similarity arises, which is used to classify (usually minimal) systems and corresponding vessels. Two vessels

$$\begin{aligned} \mathfrak{V} &= (A_1(t_2), F(t_2, t_2^0), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{H}_{t_2}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*) \\ \check{\mathfrak{V}} &= (\check{A}_1(t_2), \check{F}(t_2, t_2^0), \check{\tilde{B}}(t_2), \check{C}(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \check{\mathcal{H}}_{t_2}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*) \end{aligned}$$

are called *gauge quasi-similar* (or *kinematically quasi-similar*), if there exists a (possibly unbounded) linear operator $T(t_2) : D(T(t_2)) \rightarrow \check{\mathcal{H}}_{t_2}$, with a dense domain $D(T(t_2)) \subseteq \mathcal{H}_{t_2}$, which is 1-1, with dense range, and satisfies the following intertwining conditions

$$\begin{cases} \check{A}_1(t_2)T(t_2) &= T(t_2)A_1(t_2), \\ \check{F}(t_2, t_2^0)T(t_2^0) &= T(t_2)F(t_2, t_2^0), \\ \check{\tilde{B}}(t_2) &= T(t_2)\tilde{B}(t_2), \\ \check{C}(t_2)T(t_2) &= C(t_2). \end{cases} \quad (3.2)$$

Moreover, we shall demand that

$$\check{\mathcal{C}}_{t_2} \subseteq D(T(t_2)), \quad F(t_2, t_2^0)D(T(t_2^0)) \subseteq D(T(t_2)). \quad (3.3)$$

These conditions are necessary in order to obtain reasonable definitions in (3.2). For example, $\check{F}(t_2, t_2^0)T(t_2^0) = T(t_2)F(t_2, t_2^0)$ requires $F(t_2, t_2^0)D(T(t_2^0)) \subseteq D(T(t_2))$. The first and the third conditions require $\text{Im } B(t_2), \text{Im } A_1(t_2) \subseteq D(T_{t_2})$, for which it is enough to demand $\check{\mathcal{C}}_{t_2} \subseteq D(T(t_2))$.

When it is the case that $D(T(t_2)) = \mathcal{H}_{t_2}$ for all t_2 , and $T(t_2)$ is everywhere defined bounded and onto (with bounded inverse as a result), we say that the vessels $\mathfrak{V}, \check{\mathfrak{V}}$ are *similar*.

Remark: 1. For the finite dimensional case $\dim \mathcal{E} < \infty$, as in the classical case the notions of similarity and of quasi-similarity coincide.

2. Given a vessel $\mathfrak{V}$ and a family of invertible bounded operators $T(t_2) : \mathcal{H}_{t_2} \rightarrow \check{\mathcal{H}}_{t_2}$ the formulas (3.2) define a new vessel $\check{\mathfrak{V}}$ that is gauge similar to $\mathfrak{V}$.

3.3 Differential vessels

Suppose that the system $I\Sigma$ defined by (3.1) has identical inner spaces $\mathcal{H}_{t_2}$ for all t_2 , i.e., $\mathcal{H}_{t_2} = \mathcal{H}$. Suppose also that the evolution semi-group $F(t_2, t_2^0)$ is absolutely continuous (for a fixed t_2^0) in the norm operator topology of $B(\mathcal{H}, \mathcal{H})$, then its generator $A_2(t_2)$ is for almost all t_2 a bounded operator and satisfies

$$A_2(t_2) = \frac{d}{dt_2}F(t_2, t_2^0)F^{-1}(t_2, t_2^0).$$

Rewriting all the vessel conditions in the differential form using $A_2(t_2)$, we obtain a *differential vessel*

$$\mathfrak{D}\mathfrak{V} = (A_1(t_2), A_2(t_2), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

which satisfy the following axioms:

$$\begin{aligned}
\frac{d}{dt_2} A_1(t_2) &= A_2(t_2)A_1(t_2) - A_1(t_2)A_2(t_2) \\
\frac{d}{dt_2} (\tilde{B}(t_2)\sigma_1(t_2)) - A_2(t_2)\tilde{B}(t_2)\sigma_1(t_2) + A_1(t_2)\tilde{B}(t_2)\sigma_2(t_2) + \tilde{B}(t_2)\gamma(t_2) &= 0 \\
\frac{d}{dt_2} (\sigma_{1*}(t_2)C(t_2)) + \sigma_{1*}(t_2)C(t_2)A_2(t_2) + \sigma_{2*}(t_2)C(t_2)A_1(t_2) + \gamma_*(t_2)C(t_2) &= 0 \\
\sigma_{1*}D &= \tilde{D}\sigma_1, \quad \sigma_{2*}D = \tilde{D}\sigma_2, \\
\tilde{D}\gamma &= \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}C\tilde{B}\sigma_2 + \sigma_{1*}D' + \gamma_*D.
\end{aligned}$$

and the following regularity assumptions, which are obtained from the assumptions 2.2, 2.3, 2.4, 2.5, 2.6 by „differentiating”

Assumption 3.4 1. *Internal regularity:* $A_1(t_2), A_2(t_2) : \mathcal{H}_{t_2} \rightarrow \mathcal{H}_{t_2}$, $B_1(t_2), B_2(t_2) : \mathcal{E} \rightarrow \mathcal{H}_{t_2}$, $C(t_2) : \mathcal{H}_{t_2} \rightarrow \mathcal{E}_*$ are bounded operators (for all t_2),

2. *Feed through regularity:* the operator $D(t_2) : \mathcal{E} \rightarrow \mathcal{E}_*$, $\tilde{D}(t_2) : \mathcal{E}_* \rightarrow \tilde{\mathcal{E}}_*$ are absolutely continuous function of t_2 ,

3. *External regularity* 2.4, 2.5,

The differential vessel is associated with the system

$$D\Sigma : \begin{cases} \frac{\partial}{\partial t_1} x(t_1, t_2) = A_1(t_2)x(t_1, t_2) + \tilde{B}(t_2) \sigma_1(t_2) u(t_1, t_2) \\ \frac{\partial}{\partial t_2} x(t_1, t_2) = A_2(t_2)x(t_1, t_2) + \tilde{B}(t_2) \sigma_2(t_2) u(t_1, t_2) \\ y(t_1, t_2) = D(t_2)u(t_1, t_2) + C(t_2)x(t_1, t_2) \end{cases} \quad (3.4)$$

and compatibility conditions for the input/output signals:

$$\begin{aligned}
\sigma_2(t_2) \frac{\partial}{\partial t_1} u(t_1, t_2) - \sigma_1(t_2) \frac{\partial}{\partial t_2} u(t_1, t_2) + \gamma(t_2)u(t_1, t_2) &= 0, \\
\sigma_{2*}(t_2) \frac{\partial}{\partial t_1} y(t_1, t_2) - \sigma_{1*}(t_2) \frac{\partial}{\partial t_2} y(t_1, t_2) + \gamma_*(t_2)y(t_1, t_2) &= 0.
\end{aligned}$$

This motivates the following definition

Definition 3.5 Vessel $\mathfrak{V}$ will be called **differentiable** if $\mathcal{H}_{t_2} = \mathcal{H}$ for all t_2 and $F(t_2, t_2^0)$ is an absolutely continuous function in the norm operator topology of $B(\mathcal{H}, \mathcal{H})$.

Then the following proposition holds

Proposition 3.3 Any vessel $\mathfrak{V}$ is gauge similar to a differentiable vessel.

Proof: Let us take $T(t_2) = F(t_2^0, t_2) : \mathcal{H}_{t_2} \rightarrow \mathcal{H}_{t_2^0}$, which is an absolutely continuous, and let us find out what kind of a vessel is obtained. First notice that $T(t_2)$ are all mappings onto the same space $\mathcal{H}_{t_2^0}$, which we denote by $\mathcal{H}_{t_2^0} = \mathcal{H}$. Further, we see that

$$\begin{cases} \check{A}_1(t_2)F(t_2^0, t_2) = F(t_2^0, t_2^0)A_1(t_2) & \Rightarrow \check{A}_1(t_2) = F(t_2^0, t_2)A_1(t_2)F(t_2, t_2^0), \\ \check{F}(t_2, t_2^0)F(t_2^0, t_2^0) = F(t_2^0, t_2^0)F(t_2, t_2^0) & \Rightarrow \check{F}(t_2, t_2^0) = I, \\ \check{\tilde{B}}(t_2) = F(t_2^0, t_2)\tilde{B}(t_2), \\ \check{C}(t_2)F(t_2^0, t_2) = C(t_2) & \Rightarrow \check{C}(t_2) = C(t_2)F(t_2, t_2^0). \end{cases}$$

Thus we obtain a differentiable vessel

$$\mathfrak{D}\mathfrak{V} = (F(t_2^0, t_2)A_1(t_2)F(t_2, t_2^0), I, F(t_2^0, t_2)\tilde{B}(t_2), C(t_2)F(t_2, t_2^0), D(t_2), \tilde{D}(t_2); \\ \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

with trivial evolution semi-group I , which is obviously absolutely continuous. $\square$

Notice that this vessel is of a very special form. Its evolution semi-group is trivial and as a result, differentiating this vessel, we shall obtain that the generator of the semi group $A_2(t_2) = 0$ is trivial. Consequently, from the Lax equation, $A_1(t_2) = A_1$ becomes a constant operator.

Let us for the completeness of presentation explicitly write down the notion of quasi similarity of two differential vessels. Given two vessels

$$\mathfrak{D}\mathfrak{V} = (A_1(t_2), A_2(t_2), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2), \gamma_*(t_2); \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

and

$$\check{\mathfrak{D}}\mathfrak{V} = (\check{A}_1(t_2), \check{A}_2(t_2), \check{\tilde{B}}(t_2), \check{C}(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2), \gamma_*(t_2); \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

we will say that they are quasi-similar if there exists a (possibly unbounded) linear operator $T(t_2) : D(T(t_2)) \rightarrow \check{\mathcal{H}}_{t_2}$, with a dense domain $D(T(t_2)) \subseteq \mathcal{H}_{t_2}$, which is 1-1, with dense range, absolutely continuous (in the norm operator topology) and satisfies the following intertwining conditions

$$\begin{cases} \check{A}_1(t_2)T(t_2) &= T(t_2)A_1(t_2), \\ \check{A}_2(t_2)T(t_2) &= T(t_2)A_2(t_2) + \frac{d}{dt_2}T(t_2), \\ \check{\tilde{B}}(t_2) &= T(t_2)\tilde{B}(t_2), \\ \check{C}(t_2)T(t_2) &= C(t_2). \end{cases} \quad (3.5)$$

We shall also demand that

$$\check{\mathcal{C}}_{t_2} \subseteq D(T(t_2)), \quad \text{Im } A_2(t_2) \subseteq D(T(t_2)). \quad (3.6)$$

If $T(t_2)$ is an invertible bounded operator, we shall say that two differential vessels are *similar*.

3.4 Separation of variables and the notion of transfer function

One of the reasons why overdetermined systems invariant in one direction are interesting is the possibility to perform a partial separation of variables. Taking all the trajectory data in the form

$$\begin{aligned} u(t_1, t_2) &= u_\lambda(t_2)e^{\lambda t_1}, \\ x(t_1, t_2) &= x_\lambda(t_2)e^{\lambda t_1}, \\ y(t_1, t_2) &= y_\lambda(t_2)e^{\lambda t_1}, \end{aligned}$$

we arrive at the notion of a transfer function. Note that $u(t_1, t_2), y(t_1, t_2)$ satisfy PDEs, but $u_\lambda(t_2), y_\lambda(t_2)$ are solutions of ODEs with a spectral parameter λ ,

$$\lambda\sigma_2(t_2)u_\lambda(t_2) - \sigma_1(t_2)\frac{\partial}{\partial t_2}u_\lambda(t_2) + \gamma(t_2)u_\lambda(t_2) = 0, \quad (3.7)$$

$$\lambda\sigma_{2*}(t_2)y_\lambda(t_2) - \sigma_{1*}(t_2)\frac{\partial}{\partial t_2}y_\lambda(t_2) + \gamma_*(t_2)y_\lambda(t_2) = 0. \quad (3.8)$$

The corresponding i/s/o system becomes

$$\begin{cases} x_\lambda(t_2) = (\lambda I - A_1(t_2))^{-1} \tilde{B}(t_2) \sigma_1(t_2) u_\lambda(t_2) \\ x(t_1, t_2) = F(t_2, \tau_2) x(t_1, \tau_2) + \int_{\tau_2}^{t_2} F(t_2, s) \tilde{B}(s) \sigma_2(s) u(t_1, s) ds \\ y_\lambda(t_2) = D(t_2) u_\lambda(t_2) + C(t_2) x_\lambda(t_2) \end{cases}$$

The output $y_\lambda(t_2) = D(t_2) u_\lambda(t_2) + C(t_2) x_\lambda(t_2)$ may be found from the first i/s/o equation:

$$y_\lambda(t_2) = S(\lambda, t_2) u_\lambda(t_2),$$

using the *transfer function*

$$S(\lambda, t_2) = D(t_2) + C(t_2)(\lambda I - A_1(t_2))^{-1} \tilde{B}(t_2) \sigma_1(t_2). \quad (3.9)$$

Here λ is outside the spectrum of $A_1(t_2)$, which is independent of t_2 by (2.2.Lax). We emphasize that $S(\lambda, t_2)$ is a function of t_2 for each λ (which is a frequency variable corresponding to t_1).

Theorem 3.4 *A transfer function $S(\lambda, t_2)$, defined by (3.9) has the following properties:*

1. *For almost all t_2 , $S(\lambda, t_2)$ is an analytic function of λ in the neighborhood of ∞ , where it satisfies:*

$$S(\infty, t_2) = D(t_2)$$

2. *For all λ , $S(\lambda, t_2)$ is an absolutely continuous function of t_2 .*

3. *For each fixed λ , multiplication by $S(\lambda, t_2)$ maps solutions of $\lambda \sigma_2(t_2) u - \sigma_1(t_2) \frac{du}{dt_2} + \gamma(t_2) u = 0$ to solutions of $\lambda \sigma_2(t_2) y - \sigma_1(t_2) \frac{dy}{dt_2} + \gamma_*(t_2) y = 0$.*

Proof: Those are easily checked properties, following from the definition of $S(\lambda, t_2)$:

$$S(\lambda, t_2) = D(t_2) + C(t_2)(\lambda I - A_1(t_2))^{-1} \tilde{B}(t_2) \sigma_1(t_2).$$

When $\lambda \rightarrow \infty$, since all the operators are bounded the second summand vanishes and we obtain $S(\infty, t_2) = D(t_2)$. Moreover, it will be an analytic function of λ , when $\lambda > \|A_1(t_2)\|$ and we obtain the first property.

In order to understand the second property let us rewrite $S(\lambda, t_2)$, using the Lax equation in the following way:

$$\begin{aligned} S(\lambda, t_2) &= D(t_2) + C(t_2)(\lambda I - A_1(t_2))^{-1} B(t_2) \sigma_1(t_2) = \\ &= D(t_2) + C(t_2)(\lambda I - F(t_2, t_2^0) A_1(t_2^0) F(t_2^0, t_2))^{-1} B(t_2) \sigma_1(t_2) = \\ &= D(t_2) + C(t_2) F(t_2, t_2^0) (\lambda I - A_1(t_2^0))^{-1} F(t_2^0, t_2) B(t_2) \sigma_1(t_2). \end{aligned}$$

The functions $C(t_2) F(t_2, t_2^0)$, $F(t_2^0, t_2) B(t_2)$, $\sigma_1(t_2)$ are absolutely continuous in appropriate spaces, thus their multiplication too and we obtain the second property.

The third property is a direct result of our construction. □

Remark: for the case $\dim \mathcal{H}_{t_2} < \infty$, we obtain that $S(\lambda, t_2)$ is a rational (off the spectrum of $A_1(t_2)$) in λ function for all t_2 .

3.5 Class $\mathcal{I}$ of intertwining functions

We saw in previous section (theorem 3.4) that transfer functions are very natural objects to study and have three important properties. Suppose that we start from two ODEs the input 3.7 and the output 3.8 and denote the fundamental solution for them by $\Phi(\lambda, t_2, t_2^0)$ and by $\Phi_*(\lambda, t_2, t_2^0)$ respectively, then

$$S(\lambda, t_2)\Phi(\lambda, t_2, t_2^0) = \Phi_*(\lambda, t_2, \tau_2)S(\lambda, t_2^0) \quad (3.10)$$

and $S(\lambda, t_2)$ satisfies the following ODE

$$\frac{\partial}{\partial t_2} S(\lambda, t_2) = \sigma_{1*}^{-1}(t_2)(\sigma_{2*}(t_2)\lambda + \gamma_*(t_2))S(\lambda, t_2) - S(\lambda, t_2)\sigma_1^{-1}(t_2)(\sigma_2(t_2)\lambda + \gamma(t_2)). \quad (3.11)$$

We recall [CoLe] that from the fundamental theory of linear differential equations that for each equation there correspond and invertible matrix (or operator) function $\phi(t_2, t_2^0)$ which obtains value I for a fixed value of $t_2 = t_2^0$ and any other solution $u(t_2)$, satisfying $u(t_2^0) = u_0$ is just of the form

$$u(t_2) = \phi(t_2, t_2^0)u_0.$$

Some of the simple properties of the fundamental matrix $\Phi(\lambda, t_2, t_2^0)$ are as follows. Notice that $\Phi(\lambda, t_2, t_2^0)$ can be replaced by $\Phi_*(\lambda, t_2, t_2^0)$ with a corresponding change of operators.

Lemma 3.5 *The fundamental matrix $\Phi(\lambda, t_2, t_2^0)$ in (3.7) satisfies:*

$$\frac{\partial}{\partial t_2} \Phi(\lambda, t_2, t_2^0) = \sigma_1^{-1}(\lambda\sigma_2(t_2) + \gamma(t_2))\Phi(\lambda, t_2, t_2^0), \quad (3.12)$$

$$\frac{\partial}{\partial t_2} \Phi^{-1}(\lambda, t_2, t_2^0) = -\Phi^{-1}(\lambda, t_2, t_2^0)\sigma_1^{-1}(\lambda\sigma_2(t_2) + \gamma(t_2)), \quad (3.13)$$

$$\frac{\partial}{\partial t_2} \Phi^*(\lambda, t_2, t_2^0) = \Phi^*(\lambda, t_2, t_2^0)(\bar{\lambda}\sigma_2^*(t_2) + \gamma^*(t_2))\sigma_1^{-1*}, \quad (3.14)$$

$$\frac{\partial}{\partial t_2} \Phi^{-1*}(\lambda, t_2, t_2^0) = -(\bar{\lambda}\sigma_2^*(t_2) + \gamma^*(t_2))\sigma_1^{-1*}\Phi^{-1*}(\lambda, t_2, t_2^0), \quad (3.15)$$

Proof: Conjugating (3.7) and using a formula for the derivative of the inverse. □

Since we will intensively work with such functions, we define their class $\mathcal{I}$ as follows

Definition 3.6 *The class*

$$\mathcal{I} = \mathcal{I}(\sigma_1, \sigma_2, \gamma, \sigma_{1*}, \sigma_{2*}, \gamma_*)$$

is a class of functions $S(\lambda, t_2)$ of two variables, which are

1. *analytic in the neighborhood of $\lambda = \infty$ for all t_2 ,*
2. *absolutely continuous as functions of t_2 for almost all λ ,*
3. *map solutions of the input ODE (3.7) with spectral parameter λ to the output ODE (3.8) with the same spectral parameter (i.e., they satisfy the equation (3.10))*

4 Main theorem of gauge quasi similarity

The following result is an analogue in our framework of the standard quasi similarity theorem for minimal systems [H, BC].

Theorem 4.1 *Assume that we are given two minimal (integral) vessels $\mathfrak{V}, \check{\mathfrak{V}}$*

$$\begin{aligned}\mathfrak{V} &= (A_1(t_2), F(t_2, t_2^0), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{H}_{t_2}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*) \\ \check{\mathfrak{V}} &= (\check{A}_1(t_2), \check{F}(t_2, t_2^0), \check{\tilde{B}}(t_2), \check{C}(t_2), \check{D}(t_2), \check{\tilde{D}}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \check{\mathcal{H}}_{t_2}, \check{\mathcal{E}}, \check{\mathcal{E}}_*, \check{\tilde{\mathcal{E}}}, \check{\tilde{\mathcal{E}}}_*)\end{aligned}$$

with transfer functions $S(\lambda, t_2)$, $\check{S}(\lambda, t_2)$. Then the vessels are gauge quasi similar iff $S(\lambda, t_2) = \check{S}(\lambda, t_2)$ in a neighborhood of $\lambda = \infty$.

Proof: The easy direction of the statement considers the case when there exists $T(t_2) : \mathcal{H}_{t_2} \rightarrow \check{\mathcal{H}}_{t_2}$, responsible for quasi-similarity, i.e., satisfying (3.2) and (3.3), then

$$\begin{aligned}S(\lambda, t_2) &= D(t_2) + C(t_2)(\lambda I - A_1(t_2))^{-1}\tilde{B}(t_2)\sigma_1(t_2) = D(t_2) + \check{C}(t_2)T(t_2)(\lambda I - A_1(t_2))^{-1}\tilde{B}(t_2)\sigma_1(t_2) = \\ &= D(t_2) + \check{C}(t_2)(\lambda I - \check{A}_1(t_2))^{-1}T(t_2)\tilde{B}(t_2)\sigma_1(t_2) = D(t_2) + \check{C}(t_2)(\lambda I - \check{A}_1(t_2))^{-1}\check{\tilde{B}}(t_2)\sigma_1(t_2) = \\ &= \check{S}(\lambda, t_2).\end{aligned}$$

For the converse, we obtain first that the values at infinity of the two functions are equal:

$$D(t_2) = \check{D}(t_2) \Rightarrow \tilde{D}(t_2) = \check{\tilde{D}}(t_2), \text{ since } \sigma_1, \sigma_{1*} \text{ are invertible.}$$

By looking at the Taylor coefficients in the power series expansions of functions $S(\lambda, t_2)$, $\check{S}(\lambda, t_2)$ at infinity, we obtain

$$C(t_2)A_1^n(t_2)\tilde{B}(t_2) = \check{C}(t_2)\check{A}_1^n(t_2)\check{\tilde{B}}(t_2), \text{ for all } n = 0, 1, 2, \dots \quad (4.1)$$

Since $\mathfrak{V}$ is approximately controllable, the set

$$\tilde{\mathcal{C}}_{t_2} = \left\{ \sum_{i=1}^N F(t_2, s_i)A_1^{n_i}(s_i)\tilde{B}(s_i)e_i \mid n_i, N \in \mathbb{N}, e_i \in \mathcal{E}, s_i \in \mathbb{R} \right\}$$

is dense in $\mathcal{H}_{t_2}$. Define next $T : \tilde{\mathcal{C}}_{t_2} \rightarrow \check{\mathcal{H}}_{t_2}$ by

$$T\left(\sum_{i=1}^N F(t_2, s_i)A_1^{n_i}(s_i)\tilde{B}(s_i)e_i\right) = \sum_{i=1}^N \check{F}(t_2, s_i)\check{A}_1^{n_i}(s_i)\check{\tilde{B}}(s_i)e_i.$$

Then T is obviously a linear transformation, provided it is well defined, i.e. we have to check that

$$0 = \sum_{i=1}^N F(t_2, s_i)A_1^{n_i}(s_i)\tilde{B}(s_i)e_i \Rightarrow 0 = \sum_{i=1}^N \check{F}(t_2, s_i)\check{A}_1^{n_i}(s_i)\check{\tilde{B}}(s_i)e_i.$$

Since by assumption $\check{\mathfrak{V}}$ is observable, to show $0 = \sum_{i=1}^N \check{F}(t_2, s_i)\check{A}_1^{n_i}(s_i)\check{\tilde{B}}(s_i)e_i$ is the same as showing that

$$\check{C}(t_2)\check{A}_1^k(t_2)\left(\sum_{i=1}^N \check{F}(t_2, s_i)\check{A}_1^{n_i}(s_i)\check{\tilde{B}}(s_i)e_i\right) = 0, \text{ for all } k = 0, 1, 2, \dots$$

This is done with the help of the following lemma

Lemma 4.2 For each t_2, s the following equality holds:

$$C(t_2)(\lambda I - A_1(t_2))^{-1}F(t_2, s)\tilde{B}(s)\sigma_1(s)e = \check{C}(t_2)(\lambda I - \check{A}_1(t_2))^{-1}\check{F}(t_2, s)\check{\tilde{B}}(s)\sigma_1(s)e$$

Proof: Simple calculations using the first vessel condition 2.5.OverD, result in

$$\begin{aligned} \frac{\partial}{\partial s}(C(t_2)(\lambda I - A_1(t_2))^{-1}F(t_2, s)\tilde{B}(s)\sigma_1(s)) &= \\ = -C(t_2)(\lambda I - A_1(t_2))^{-1}F(t_2, s)\tilde{B}(s)[\sigma_2(s)\lambda + \gamma(s)] + C(t_2)F(t_2, s)\tilde{B}(s)\sigma_2(s), \end{aligned}$$

Remember that the function $\Phi(\lambda, t_2, t_2^0)$ satisfies (3.13), so using variation of coefficients

$$C(t_2)(\lambda I - A_1(t_2))^{-1}F(t_2, s)\tilde{B}(s)\sigma_1(s) = K(\lambda, t_2, s)\Phi^{-1}(\lambda, t_2, s)$$

where

$$\frac{\partial}{\partial s}K(\lambda, t_2, s) = C(t_2)F(t_2, s)\tilde{B}(s)\sigma_2(s)\Phi(\lambda, t_2, s).$$

Particularly, $K(\lambda, t_2, s)$ is

$$\begin{aligned} K(\lambda, t_2, s) &= K(\lambda, t_2^0, s) + \int_{t_2^0}^{t_2} \frac{\partial}{\partial s}K(\lambda, t_2, s)ds = \\ &= K(\lambda, t_2^0, s) + \int_{t_2^0}^{t_2} C(t_2)F(t_2, s)\tilde{B}(s)\sigma_2(s)\Phi(\lambda, t_2, s)ds \end{aligned}$$

and all its poles are at the first term $K(\lambda, t_2^0, s)$. The same considerations, applied to $\check{C}(t_2)(\lambda I - \check{A}_1(t_2))^{-1}\check{F}(t_2, s)\check{\tilde{B}}(s)\sigma_1(s)$ results in a function $\check{K}(\lambda, t_2, s)$, whose poles are also at the term $\check{K}(\lambda, t_2^0, s)$:

$$\check{K}(\lambda, t_2, s) = \check{K}(\lambda, t_2^0, s) + \int_{t_2^0}^{t_2} \check{C}(t_2)\check{F}(t_2, s)\check{\tilde{B}}(s)\sigma_2(s)\Phi(\lambda, t_2, s)ds.$$

Then

$$\begin{aligned} &C(t_2)(\lambda I - A_1(t_2))^{-1}F(t_2, s)\tilde{B}(s)\sigma_1(s) - \check{C}(t_2)(\lambda I - \check{A}_1(t_2))^{-1}\check{F}(t_2, s)\check{\tilde{B}}(s)\sigma_1(s) = \\ &= [K(\lambda, t_2, s) - \check{K}(\lambda, t_2, s)]\Phi^{-1}(\lambda, t_2, s) = \\ &= [K(\lambda, t_2, t_2) + \int_{t_2}^s \frac{\partial}{\partial y}K(\lambda, t_2, y)dy - \check{K}(\lambda, t_2, t_2) - \int_{t_2}^s \frac{\partial}{\partial y}\check{K}(\lambda, t_2, y)dy]\Phi^{-1}(\lambda, t_2, s) = \\ &= [\int_{t_2}^s \frac{\partial}{\partial y}K(\lambda, t_2, y)dy - \int_{t_2}^s \frac{\partial}{\partial y}\check{K}(\lambda, t_2, y)dy]\Phi^{-1}(\lambda, t_2, s), \end{aligned}$$

in other words, this difference is an entire function of λ . On the other hand, two functions

$$C(t_2)(\lambda I - A_1(t_2))^{-1}F(t_2, s)\tilde{B}(s)\sigma_1(s), \quad \check{C}(t_2)(\lambda I - \check{A}_1(t_2))^{-1}\check{F}(t_2, s)\check{\tilde{B}}(s)\sigma_1(s)$$

are zero at infinity (i.e., globally bounded). Taking a pairing with an arbitrary linear functional and the operator applied to arbitrary vector, by Liouville's theorem this difference is constant and is equal to the value at infinity for each such pairing. Thus the operator itself is zero. $\square$

One of the consequences of this theorem is that Taylor coefficients around infinity of the functions

$$C(t_2)(\lambda I - A_1(t_2))^{-1}F(t_2, s)\tilde{B}(s)\sigma_1(s), \quad \check{C}(t_2)(\lambda I - \check{A}_1(t_2))^{-1}\check{F}(t_2, s)\check{\tilde{B}}(s)\sigma_1(s)$$

are equal, and consequently,

$$C(t_2)A_1(t_2)^n F(t_2, s) \tilde{B}(s) \sigma_1(s) = \check{C}(t_2) \check{A}_1(t_2)^n \check{F}(t_2, s) \check{\tilde{B}}(s) \sigma_1(s)$$

Using this result, the fact that $T(t_2)$ is well defined is immediate, because

$$\begin{aligned} \check{C}(t_2) \check{A}_1^k(t_2) (\sum_{i=1}^N \check{F}(t_2, s_i) \check{A}_1^{n_i}(s_i) \check{\tilde{B}}(s_i) e_i) &= \sum_{i=0}^N \check{C}(t_2) \check{F}(t_2, s_i) \check{A}_1^{n_i+k}(s_i) \check{\tilde{B}}(s_i) e_i = \\ &= \sum_{i=0}^N C(t_2) F(t_2, s_i) A_1^{n_i+k}(s_i) \tilde{B}(s_i) e_i = C(t_2) A_1^k(t_2) (\sum_{i=0}^N F(t_2, s_i) A_1^{n_i}(s_i) \tilde{B}(s_i) e_i) = C(t_2) A^k(t_2) 0 = 0. \end{aligned}$$

One checks that T is one-to-one by using the observability of $\mathfrak{V}$:

$$\text{Ker } T = \bigcap_{n \in \mathbb{N}, s \in \mathbb{R}} \text{Ker } C(s) A_1^n(s) F(s, t_2) = \tilde{\mathcal{O}}_{t_2}^\perp,$$

which is trivial by assumption of minimality. That T has dense range follows from the approximate controllability of $\mathfrak{V}$. This finishes the proof. $\square$

Since the notions of similarity and quasi-similarity are identical for finite dimensional vessels, we obtain

Corollary 4.3 *Two finite dimensional vessels (with rational in λ transfer functions) are gauge similar, if and only if, the transfer functions are identical at the neighborhood of $\lambda = \infty$.*

5 Adjoint system

The notion of the adjoint system is very useful in system theory. It is obtained from a simple observation that applying adjoint to the vessel conditions gives rise to a new set of conditions on adjoint operators, which are almost vessel conditions. Moreover $(\Sigma^*)^*$ is actually Σ by a trivial change of coordinates $x \rightarrow -x$ on the state space. Here is the precise definition. Given a system in the differential form

$$\mathfrak{D}\Sigma : \begin{cases} \frac{\partial}{\partial t_1} x(t_1, t_2) = A_1(t_2) x(t_1, t_2) + \tilde{B}(t_2) \sigma_1(t_2) u(t_1, t_2) \\ \frac{\partial}{\partial t_2} x(t_1, t_2) = A_2(t_2) x(t_1, t_2) + \tilde{B}(t_2) \sigma_2(t_2) u(t_1, t_2) \\ y(t_1, t_2) = D(t_2) u(t_1, t_2) + C(t_2) x(t_1, t_2) \end{cases} \quad (5.1)$$

and associated vessel

$$\mathfrak{V} = (A_1(t_2), A_2(t_2), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2) \gamma_*(t_2); \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

it is natural to introduce the *adjoint system*:

$$D\Sigma^* : \begin{cases} -\frac{\partial}{\partial t_1} x_*(t_1, t_2) = A_1^*(t_2) x_*(t_1, t_2) + C^*(t_2) \sigma_{1*}^* u_*(t_1, t_2) \\ -\frac{\partial}{\partial t_2} x_*(t_1, t_2) = A_2^*(t_2) x_*(t_1, t_2) + C^*(t_2) \sigma_{2*}^* u_*(t_1, t_2) \\ y_*(t_1, t_2) = \tilde{B}^* x_*(t_1, t_2) + \tilde{D}^*(t_2) u_*(t_1, t_2), \end{cases} \quad (5.2)$$

which is associated to the vessel $\mathfrak{V}^*$ given by

$$\mathfrak{V}^* = (-A_1^*, -A_2^*, -C^*, \tilde{B}^*, \tilde{D}^*, D^*; \sigma_{1*}^*, \sigma_{2*}^*, -\gamma_*^* - \frac{d}{dt_2} \sigma_{1*}^*, \sigma_1^*, \sigma_2^*, -\gamma_*^* - \frac{d}{dt_2} \sigma_1^*; \mathcal{H}, \tilde{\mathcal{E}}_*, \tilde{\mathcal{E}}_*, \mathcal{E}_*, \mathcal{E}),$$

where all the operators are functions of t_2 and satisfy the following axioms:

$$\begin{aligned} \frac{d}{dt_2} A_1^* &= A_1^* A_2^* - A_2^* A_1^* \\ -\frac{d}{dt_2} (C^* \sigma_{1*}^*) - A_2^* C^* \sigma_{1*}^* + A_1^* C^* \sigma_{2*}^* + C^* (\gamma^* + \frac{d}{dt_2} \sigma_{1*}^*) &= 0 \\ \frac{d}{dt_2} (\sigma_1^* \tilde{B}^*) - \sigma_1^* \tilde{B}^* A_2^* + \sigma_2^* \tilde{B}^* A_1^* + \gamma^* \tilde{B}^* &= 0 \\ \sigma_1^* \tilde{D}^* &= D^* \sigma_{1*}^*, \quad \sigma_2^* \tilde{D}^* = D^* \sigma_{2*}^* \\ D^* (-\gamma^* - \frac{d}{dt_2} \sigma_{1*}^*) &= -\sigma_2^* \tilde{B}^* C^* \sigma_{1*}^* + \sigma_1^* \tilde{B}^* C^* \sigma_{2*}^* - \sigma_1^* \frac{d}{dt_2} \tilde{D}^* - (\gamma^* + \frac{d}{dt_2} \sigma_{1*}^*) \tilde{D}^*. \end{aligned}$$

Moreover, the transfer function of the adjoint vessel $S_*(\mu, t_2)$ maps solutions of the *adjoint input* ODE

$$[\sigma_{2*}^* \mu - \sigma_{1*}^* \frac{d}{dt_2} - \gamma^* - \frac{d}{dt_2} \sigma_{1*}^*] u_*(t_2) = 0 \quad (5.3)$$

with the spectral parameter μ to solutions of the *adjoint output* ODE

$$[\sigma_2^* \mu - \sigma_1^* \frac{d}{dt_2} - \gamma^* - \frac{d}{dt_2} \sigma_1^*] y_*(t_2) = 0 \quad (5.4)$$

with the same spectral parameter. In the language of fundamental matrices, if one denotes the fundamental solution for $u_*(t_2), y_*(t_2)$ as $\Psi(\mu, t_2, t_2^0)$ and $\Psi_*(\mu, t_2, t_2^0)$, respectively, then (similarly to (3.10))

$$S_*(\mu, t_2) \Psi(\mu, t_2, \tau_2) = \Psi_*(\mu, t_2, \tau_2) S_*(\mu, \tau_2)$$

Notice also that the equation for $S_*(\lambda, t_2)$ similar to (3.9) is:

$$S_*(\mu, t_2) = \tilde{D}^* - \tilde{B}^* (\mu I + A_1^*)^{-1} C^* \sigma_{1*}^*$$

And as in the case of constant operators, one obtains that $\mathfrak{V}^*$ is a vessel iff $\mathfrak{V}$ is. And as we mentioned before, $\mathfrak{V}^{**}$ is the same as $\mathfrak{V}$ after a trivial change of coordinates $x \rightarrow -x$ on the state space.

Remarks:

1. It is easy to check that $\sigma_{1*}^* \Phi_*^{-1*}(\lambda, t_2, t_2^0)$ and $\Psi(-\bar{\lambda}, t_2, t_2^0)$ satisfy the same differential equation. Since they are fundamental matrices it is possible iff

$$\sigma_{1*}^{-1*} \Phi_*^{-1*}(\lambda, t_2, t_2^0) = \Psi(-\bar{\lambda}, t_2, t_2^0) \sigma_{1*}^{-1*} \quad (5.5)$$

$$\sigma_1^{-1*} \Phi^{-1*}(\lambda, t_2, t_2^0) = \Psi_*(-\bar{\lambda}, t_2, t_2^0) \sigma_1^{-1*} \quad (5.6)$$

2. This relation between Φ and Ψ fundamental matrices means that the following relation between transfer functions has to be satisfied:

$$S(\lambda, t_2) = \sigma_{1*}^{-1} S^*(-\bar{\lambda}, t_2) \sigma_1 \quad (5.7)$$

One can easily verify this formula directly, using the vessel conditions and the formulas for $S(\lambda, t_2)$, $S^*(-\bar{\lambda}, t_2)$:

$$\begin{aligned} \sigma_{1*}^{-1} S^*(-\bar{\lambda}, t_2) \sigma_1 &= \sigma_{1*}^{-1} [\tilde{D}^* - \tilde{B}^* (-\bar{\lambda} I + A_1^*)^{-1} C^* \sigma_{1*}^*]^* \sigma_1 = \\ &= \sigma_{1*}^{-1} [\tilde{D} - \sigma_{1*} C (-\lambda I + A_1)^{-1} \tilde{B}] \sigma_1 = \sigma_{1*}^{-1} \tilde{D} \sigma_1 - C (-\lambda I + A_1)^{-1} \tilde{B} \sigma_1 = \\ &= D + C (\lambda I - A_1)^{-1} \tilde{B} \sigma_1 = S(\lambda, t_2). \end{aligned}$$

3. For values of λ outside of the spectrum of $A_1(t_2)$ (which is independent of t_2), we claim that $S(\lambda, t_2)$ is invertible iff $S^*(-\bar{\lambda}, t_2)$ is and from (5.7) we conclude that

$$S(\lambda, t_2)^{-1} = \sigma_{1*}^{-1} S_*^{-1*}(-\bar{\lambda}, t_2) \sigma_{1*}$$

6 System and vessel operations

As in the classical case we develop basic system operations in our setting, which will be of great importance in solving factorization problems for transfer functions.

6.1 Cascade connection of systems

Suppose we are given two vessels

$$\begin{aligned} \mathfrak{I}\mathfrak{V}' &= (A'_1(t_2), F'(t_2, t_2^0), \tilde{B}'(t_2), C'(t_2), D'(t_2), \tilde{D}'(t_2); \\ &\quad \sigma'_1(t_2), \sigma'_2(t_2), \gamma'(t_2), \sigma'_{1*}(t_2), \sigma'_{2*}(t_2), \gamma'_*(t_2); \mathcal{H}'_{t_2}, \mathcal{E}', \mathcal{E}'_*, \tilde{\mathcal{E}}', \tilde{\mathcal{E}}'_*), \\ \mathfrak{I}\mathfrak{V}'' &= (A''_1(t_2), F''(t_2, t_2^0), \tilde{B}''(t_2), C''(t_2), D''(t_2), \tilde{D}''(t_2); \\ &\quad \sigma''_1(t_2), \sigma''_2(t_2), \gamma''(t_2), \sigma''_{1*}(t_2), \sigma''_{2*}(t_2), \gamma''_*(t_2); \mathcal{H}''_{t_2}, \mathcal{E}'', \mathcal{E}''_*, \tilde{\mathcal{E}}'', \tilde{\mathcal{E}}''_*). \end{aligned} \quad (6.1)$$

and the corresponding systems $I\Sigma', I\Sigma''$, defined in (3.1). We want to generate a new system $I\Sigma$ by feeding in the output of the first system $I\Sigma'$ as the input for the second system $I\Sigma''$. To this end we assume the output spaces of the first system are the same as the input spaces of the second system (as in the case of the classical cascade connection) but also that *the corresponding compatibility conditions hold*:

$$\sigma'_{1*}(t_2) = \sigma''_1(t_2), \quad \sigma'_{2*}(t_2) = \sigma''_2(t_2), \quad \gamma'_*(t_2) = \gamma''_*(t_2), \quad \tilde{\mathcal{E}}' = \mathcal{E}'', \quad \tilde{\mathcal{E}}'_* = \mathcal{E}''_* \quad (6.2)$$

Thus we obtain the following system of equations

$$\begin{aligned} I\Sigma' : \begin{cases} \frac{\partial}{\partial t_1} x'(t_1, t_2) = A'_1(t_2)x'(t_1, t_2) + \tilde{B}'(t_2)\sigma'_1(t_2)u(t_1, t_2) \\ x'(t_1, t_2) = F'(t_2, t_2^0)x'(t_1, t_2^0) + \int_{t_2^0}^{t_2} F'(t_2, s)\tilde{B}'(s)\sigma'_2(s)u(t_1, s)ds \\ y'(t_1, t_2) = C'(t_2)x'(t_1, t_2) + D'(t_2)u(t_1, t_2) \end{cases} \\ I\Sigma'' : \begin{cases} \frac{\partial}{\partial t_1} x''(t_1, t_2) = A''_1(t_2)x''(t_1, t_2) + \tilde{B}''(t_2)\sigma'_{1*}(t_2)u''(t_1, t_2) \\ x''(t_1, t_2) = F''(t_2, t_2^0)x''(t_1, t_2^0) + \int_{t_2^0}^{t_2} F''(t_2, s)\tilde{B}''(s)\sigma'_{2*}(s)u''(t_1, s)ds \\ y(t_1, t_2) = C''(t_2)x''(t_1, t_2) + D''(t_2)u''(t_1, t_2) \end{cases} \end{aligned}$$

Setting $u''(t_2) = y'(t_2)$, eliminating it and simplifying we get

$$I\Sigma : \begin{cases} \frac{\partial}{\partial t_1} \begin{bmatrix} x'(t_1, t_2) \\ x''(t_1, t_2) \end{bmatrix} = \begin{bmatrix} A'_1(t_2) & 0 \\ \tilde{B}''(t_2)\sigma'_1(t_2)C'(t_2) & A''_1(t_2) \end{bmatrix} \begin{bmatrix} x'(t_1, t_2) \\ x''(t_1, t_2) \end{bmatrix} + \begin{bmatrix} B'(t_2) \\ \tilde{B}''(t_2)\tilde{D}'(t_2) \end{bmatrix} \sigma'_1 u(t_1, t_2) \\ \begin{bmatrix} x'(t_1, t_2) \\ x''(t_1, t_2) \end{bmatrix} = \begin{bmatrix} F'(t_2, t_2^0) & 0 \\ \int_{t_2^0}^{t_2} F''(t_2, s)\tilde{B}''(s)\sigma'_2(s)C'(s)F'(s, t_2^0)ds & F''(t_2, t_2^0) \end{bmatrix} \begin{bmatrix} x'(t_1, t_2^0) \\ x''(t_1, t_2^0) \end{bmatrix} + \\ + \int_{t_2^0}^{t_2} \begin{bmatrix} F'(t_2, s) & 0 \\ \int_s^{t_2} F''(t_2, y)\tilde{B}''(y)\sigma'_2(y)C'(y)F'(y, t_2^0)dy & F''(t_2, s) \end{bmatrix} \begin{bmatrix} \tilde{B}'(s) \\ \tilde{B}''(s)\tilde{D}'(s) \end{bmatrix} \sigma'_2(s)u(t_1, s)ds \\ y(t_1, t_2) = \begin{bmatrix} D''(t_2)C'(t_2) & C''(t_2) \end{bmatrix} \begin{bmatrix} x'(t_1, t_2^0) \\ x''(t_1, t_2^0) \end{bmatrix} + D''(t_2)D'(t_2)u(t_1, t_2) \end{cases}$$

Thus the corresponding vessel of this system is the following

$$\mathfrak{V} = \left(\begin{bmatrix} A'_1(t_2) & 0 \\ \tilde{B}''(t_2)\sigma'_1(t_2)C'(t_2) & A''_1(t_2) \end{bmatrix}, \begin{bmatrix} F'(t_2, t_2^0) & 0 \\ \int_{t_2^0}^{t_2} F''(t_2, s)\tilde{B}''(s)\sigma'_2(s)C'(s)F'(s, t_2^0)ds & F''(t_2, t_2^0) \end{bmatrix}, \right. \\ \left. \begin{bmatrix} B'(t_2) \\ \tilde{B}''(t_2)\tilde{D}'(t_2) \end{bmatrix}, \begin{bmatrix} D''(t_2)C'(t_2) & C''(t_2) \end{bmatrix}, D''(t_2)D'(t_2), \tilde{D}''(t_2)\tilde{D}'(t_2); \right. \\ \left. \sigma'_1(t_2), \sigma'_2(t_2), \gamma'(t_2), \sigma''_{1*}(t_2), \sigma''_{2*}(t_2), \gamma''_*(t_2); \mathcal{H}'_{t_2} \oplus \mathcal{H}''_{t_2}, \mathcal{E}', \mathcal{E}''_*, \tilde{\mathcal{E}}'', \tilde{\mathcal{E}}''_* \right) \quad (6.3)$$

Last evaluation suggests that the system $I\Sigma$ with compatibility conditions $u'(t_1, t_2) = y''(t_1, t_2)$ indeed corresponds to a vessel

Theorem 6.1 *Given two vessels $\mathfrak{V}'$, $\mathfrak{V}''$, defined in (6.1) and satisfying compatibility conditions (6.2)*

$$\sigma'_{1*}(t_2) = \sigma''_1(t_2), \quad \sigma'_{2*}(t_2) = \sigma''_2(t_2), \quad \gamma'_*(t_2) = \gamma''(t_2), \quad \tilde{\mathcal{E}}' = \mathcal{E}'', \quad \tilde{\mathcal{E}}'_* = \mathcal{E}''_*$$

their cascade connection $\mathfrak{V}$, defined in (6.3) is a vessel. Transfer functions $S'(\lambda, t_2)$, $S''(\lambda, t_2)$, $S(\lambda, t_2)$ of the vessels $\mathfrak{V}'$, $\mathfrak{V}''$, $\mathfrak{V}$ respectively satisfy the following relation

$$S(\lambda, t_2) = S''(\lambda, t_2)S'(\lambda, t_2)$$

Proof: We have already seen that $\mathfrak{V}$ is a vessel, provided $\mathfrak{V}'$, $\mathfrak{V}''$ are. In order to see the formula for transfer functions, we feed in the output $y'_\lambda(t_2)$ of the first system as the input $u''_\lambda(t_2)$ for the second system (recall definitions in section 3.4). Then $y'_\lambda(t_2) = S(\lambda, t_2)u'_\lambda(t_2)$ is the input ($u''_\lambda(t_2) = y'_\lambda(t_2)$) for the second system and

$$y''_\lambda(t_2) = S''(\lambda, t_2)u''_\lambda(t_2) = S''(\lambda, t_2)y'_\lambda(t_2) = S''(\lambda, t_2)S'(\lambda, t_2)u'_\lambda(t_2).$$

We conclude that the transfer function $S(\lambda, t_2)$ for the composite system $I\Sigma$ is simply the product of the transfer functions of the component systems:

$$S(\lambda, t_2) = S'(\lambda, t_2)S''(\lambda, t_2). \quad (6.4)$$

□

The following theorem is the analogue of theorem 6.1 for differential vessels. It can be either deduced from theorem 6.1 by differentiation, or the formulas can be obtained directly by writing the systems equations in the differential form and the result established directly by algebraic manipulations

Theorem 6.2 *Suppose that we are given two differential vessels*

$$\mathfrak{V}' = (A'_1(t_2), A'_2(t_2), \tilde{B}'(t_2), C'(t_2), D'(t_2), \tilde{D}'(t_2); \\ \sigma'_1(t_2), \sigma'_2(t_2), \gamma'(t_2), \sigma'_{1*}(t_2), \sigma'_{2*}(t_2), \gamma'_*(t_2); \mathcal{H}', \mathcal{E}', \mathcal{E}'_*, \tilde{\mathcal{E}}', \tilde{\mathcal{E}}'_*)$$

and

$$\mathfrak{V}'' = (A''_1(t_2), A''_2(t_2), \tilde{B}''(t_2), C''(t_2), D''(t_2), \tilde{D}''(t_2); \\ \sigma''_1(t_2), \sigma''_2(t_2), \gamma''(t_2), \sigma''_{1*}(t_2), \sigma''_{2*}(t_2), \gamma''_*(t_2); \mathcal{H}'', \mathcal{E}'', \mathcal{E}''_*, \tilde{\mathcal{E}}'', \tilde{\mathcal{E}}''_*).$$

satisfying the compatibility conditions (6.2), then the following collection

$$\mathfrak{D}\mathfrak{V} = \left(\begin{bmatrix} A'_1(t_2) & 0 \\ \tilde{B}''_1(t_2)\sigma_1(t_2)C'(t_2) & A'_1(t_2) \end{bmatrix}, \begin{bmatrix} A'_2(t_2) & 0 \\ \tilde{B}''_2(t_2)\sigma_2(t_2)C'(t_2) & A'_2(t_2) \end{bmatrix}, \right. \\ \left. \begin{bmatrix} \tilde{B}'(t_2) \\ \tilde{B}''(t_2)\tilde{D}'(t_2) \end{bmatrix}, \begin{bmatrix} D''(t_2)C'(t_2) & C''(t_2) \end{bmatrix}, D''(t_2)D'(t_2), \tilde{D}''(t_2)\tilde{D}'(t_2); \right. \\ \left. \sigma'_1(t_2), \sigma'_2(t_2), \gamma'(t_2), \sigma'_{1*}(t_2), \sigma'_{2*}(t_2), \gamma''_*(t_2)(t_2); \mathcal{H}' \oplus \mathcal{H}'', \mathcal{E}', \mathcal{E}'_*, \tilde{\mathcal{E}}'', \tilde{\mathcal{E}}''_* \right)$$

is a vessel called cascade connection of the vessels $\mathfrak{D}\mathfrak{V}'$, $\mathfrak{D}\mathfrak{V}''$. The transfer functions of the corresponding systems satisfy the formula (6.4).

6.2 Inversion of systems

For the classical case [BGK], if the feed through operator D is invertible, then one can define an inverse system having a transfer function equal to the reciprocal of the transfer function of the original system. The analogue for t_1 invariant overdetermined 2D system is as follows. Suppose that for the vessel in the differential form

$$\mathfrak{D}\mathfrak{V} = (A_1(t_2), A_2(t_2), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

both $D : \mathcal{E} \rightarrow \mathcal{E}_*$ and $\tilde{D} : \tilde{\mathcal{E}} \rightarrow \tilde{\mathcal{E}}_*$ are invertible. Then we may solve u in terms of y from the last system equation

$$D\Sigma : \begin{cases} \frac{\partial}{\partial t_1}x(t_1, t_2) = A_1(t_2)x(t_1, t_2) + \tilde{B}(t_2) \sigma_1(t_2) u(t_1, t_2) \\ \frac{\partial}{\partial t_2}x(t_1, t_2) = A_2(t_2)x(t_1, t_2) + \tilde{B}(t_2) \sigma_2(t_2) u(t_1, t_2) \\ y(t_1, t_2) = D(t_2)u(t_1, t_2) + C(t_2)x(t_1, t_2) \end{cases}$$

by

$$u(t_1, t_2) = -D^{-1}(t_2)C(t_2)x(t_1, t_2) + D^{-1}(t_2)y(t_1, t_2)$$

and plug it back to get a system $D\Sigma^\times$ having the property that (u, x, y) is a trajectory for $D\Sigma$ if and only if (y, x, u) is a trajectory for $D\Sigma^\times$:

$$D\Sigma^\times : \begin{cases} \frac{\partial}{\partial t_1}x(t_1, t_2) = (A_1(t_2) - \tilde{B}\sigma_1 D^{-1}(t_2)C(t_2))x(t_1, t_2) + \tilde{B}(t_2) \sigma_1(t_2) D^{-1}(t_2) y(t_1, t_2) \\ \frac{\partial}{\partial t_2}x(t_1, t_2) = (A_2(t_2) - \tilde{B}\sigma_2 D^{-1}(t_2)C(t_2))x(t_1, t_2) + \tilde{B}(t_2) \sigma_2(t_2) D^{-1}(t_2) y(t_1, t_2) \\ u(t_1, t_2) = -D^{-1}(t_2)C(t_2)x(t_1, t_2) + D^{-1}(t_2)y(t_1, t_2) \end{cases}$$

The linkage conditions (2.10.Link) means that

$$\tilde{D}^{-1}\sigma_{1*} = \sigma_1 D^{-1}, \quad \tilde{D}^{-1}\sigma_{2*} = \sigma_2 D^{-1},$$

so that this system can be rearranged somewhat to

$$D\Sigma^\times : \begin{cases} \frac{\partial}{\partial t_1}x(t_1, t_2) = (A_1(t_2) - \tilde{B}\sigma_1 D^{-1}(t_2)C(t_2))x(t_1, t_2) + \tilde{B}(t_2)\tilde{D}^{-1}(t_2)\sigma_{1*}(t_2) y(t_1, t_2) \\ \frac{\partial}{\partial t_2}x(t_1, t_2) = (A_2(t_2) - \tilde{B}\sigma_2 D^{-1}(t_2)C(t_2))x(t_1, t_2) + \tilde{B}(t_2)\tilde{D}^{-1}(t_2)\sigma_{2*}(t_2) y(t_1, t_2) \\ u(t_1, t_2) = -D^{-1}(t_2)C(t_2)x(t_1, t_2) + D^{-1}(t_2)y(t_1, t_2) \end{cases}$$

This suggests the following theorem

Theorem 6.3 *The following collection*

$$\mathfrak{V}^\times = (A_1(t_2)^\times, A_2^\times(t_2), \tilde{B}^\times(t_2), C^\times(t_2), D^\times(t_2), \tilde{D}^\times(t_2); \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2), \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2); \mathcal{H}, \mathcal{E}_*, \mathcal{E}, \tilde{\mathcal{E}}_*, \tilde{\mathcal{E}})$$

where

$$\begin{aligned} A_1(t_2)^\times &= A_1(t_2) - \tilde{B}\sigma_1 D^{-1}(t_2)C(t_2), \quad A_2^\times(t_2) = A_2(t_2) - \tilde{B}\sigma_2 D^{-1}(t_2)C(t_2), \\ \tilde{B}^\times(t_2) &= \tilde{B}(t_2)\tilde{D}^{-1}(t_2), \quad C^\times(t_2) = -D^{-1}(t_2)C(t_2), \\ D^\times(t_2) &= D^{-1}(t_2), \quad \tilde{D}^\times(t_2) = \tilde{D}^{-1}(t_2) \end{aligned}$$

is a vessel with transfer function $S^\times(\lambda, t_2)$ equal to the inverse of the transfer function $S(\lambda, t_2)$ of the vessel $\mathfrak{V}$.

Proof: We have to show that all the vessel conditions hold. Let us omit the t_2 dependence of all the operators

- Lax equation: $\frac{d}{dt_2}A_1^\times = A_1^\times A_2^\times - A_2^\times(t_2)A_1^\times(t_2)$.

$$\frac{d}{dt_2}A_1^\times = \frac{d}{dt_2}[A_1 - \tilde{B}\sigma_1 D^{-1}C] = \frac{d}{dt_2}A_1 - \frac{d}{dt_2}[\tilde{B}\sigma_1 D^{-1}C] = \frac{d}{dt_2}A_1 - \frac{d}{dt_2}[\tilde{B}\sigma_1]D^{-1}C - \tilde{B}\sigma_1 \frac{d}{dt_2}[D^{-1}C]$$

On the other hand,

$$\begin{aligned} A_1^\times A_2^\times - A_2^\times(t_2)A_1^\times(t_2) &= (A_1 - \tilde{B}\sigma_1 D^{-1}C)(A_2 - \tilde{B}\sigma_2 D^{-1}C) - (A_2 - \tilde{B}\sigma_2 D^{-1}C)(A_1 - \tilde{B}\sigma_1 D^{-1}C) = \\ &= A_1 A_2 - A_2 A_1 + \\ &\quad + [-A_1 \tilde{B}\sigma_2 + A_2 \tilde{B}\sigma_1 - \tilde{B}\sigma_2 D^{-1}C \tilde{B}\sigma_1]D^{-1}C + \\ &\quad + \tilde{B}\sigma_1 [-D^{-1}C A_2 + \sigma_1^{-1} \sigma_2 D^{-1}C A_1 + D^{-1}C \tilde{B}\sigma_2 D^{-1}C] \end{aligned}$$

Using now linkage conditions (2.10.Link) for the original vessel $\mathfrak{V}$ the result follows.

- Input vessel condition: $\frac{d}{dt_2}(\tilde{B}^\times \sigma_{1*}) - A_2^\times \tilde{B}^\times \sigma_{1*} + A_1^\times \tilde{B}^\times \sigma_{2*} + \tilde{B}^\times \gamma_* = 0$. We first simplify the expression with derivative:

$$\frac{d}{dt_2}(\tilde{B}^\times \sigma_{1*}) = \frac{d}{dt_2}(\tilde{B}\tilde{D}^{-1}\sigma_{1*}) = \frac{d}{dt_2}(\tilde{B}\sigma_1 D^{-1}) = \frac{d}{dt_2}(\tilde{B}\sigma_1)D^{-1} + \tilde{B}\sigma_1 \frac{d}{dt_2}(D^{-1})$$

and the other elements are

$$\begin{aligned} -A_2^\times \tilde{B}^\times \sigma_{1*} + A_1^\times \tilde{B}^\times \sigma_{2*} + \tilde{B}^\times \gamma_* &= \\ &= -[A_2 - \tilde{B}\sigma_2 D^{-1}C]\tilde{B}\tilde{D}^{-1}\sigma_{1*} + [A_1 - \tilde{B}\sigma_1 D^{-1}C]\tilde{B}\tilde{D}^{-1}\sigma_{2*} + \tilde{B}\tilde{D}^{-1}\gamma_* = \\ &= [-A_2 \tilde{B}\sigma_1 + A_1 \tilde{B}\sigma_2 - \tilde{B}\tilde{D}^{-1}\sigma_{2*}C\tilde{B}\sigma_1 - \tilde{B}\tilde{D}^{-1}\sigma_{1*}C\tilde{B}\sigma_2]D^{-1} + \tilde{B}\tilde{D}^{-1}\gamma_* \end{aligned}$$

and using now the linkage condition we obtain that their sum is zero.

- Output vessel condition: $\frac{d}{dt_2}(\sigma_1 C^\times) + \sigma_1 C^\times A_2^\times + \sigma_2 C^\times A_1^\times + \gamma C^\times = 0$ is similar to the input vessel condition.
- Linkage conditions:

$$\begin{aligned} \sigma_1 D^\times &= \tilde{D}^\times \sigma_{1*}, \quad \sigma_2 D^\times = \tilde{D}^\times \sigma_{2*}, \\ \tilde{D}^\times \gamma_* &= \sigma_2 C^\times \tilde{B}^\times \sigma_{1*} - \sigma_1 C^\times \tilde{B}^\times \sigma_{2*} + \sigma_1 \frac{d}{dt_2}D^\times + \gamma D^\times. \end{aligned}$$

This is an immediate result of the linkage condition for the original vessel, rearranging the elements and multiplying by inverse of D .

□

The analogue of the last theorem for vessels in the integral form can be obtained by integrating the corresponding formulas of differential vessels. The result is as follows

Theorem 6.4 *Given the integral vessel $\mathfrak{V}$*

$$\mathfrak{V} = (A_1(t_2), F(t_2, t_2^0), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \\ \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2), \gamma_*(t_2); \mathcal{H}_{t_2}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*)$$

the following collection is a vessel (called inverse)

$$\mathfrak{V}^\times = (A_1^\times(t_2), F^\times(t_2, t_2^0), \tilde{B}(t_2)\tilde{D}^{-1}(t_2), -D^{-1}(t_2)C(t_2), D^{-1}(t_2), \tilde{D}^{-1}(t_2); \\ \sigma_{1*}(t_2), \sigma_{2*}(t_2), \gamma_*(t_2), \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2); \mathcal{H}, \mathcal{E}_*, \mathcal{E}, \tilde{\mathcal{E}}_*, \tilde{\mathcal{E}}),$$

where

$$\begin{aligned} A_1(t_2)^\times &= A_1(t_2) - \tilde{B}\sigma_1 D^{-1}(t_2)C(t_2), \\ F^\times(t_2, t_2^0) &= F(t_2, t_2^0) - \int_{t_2^0}^{t_2} F(t_2, t_2^1) \tilde{B}(t_2^1) \sigma_2(t_2^1) D^{-1}(t_2^1) C(t_2^1) F(t_2^1, t_2^0) dt_2^1 - \dots - \\ &\quad \int_{t_2^0}^{t_2} \int_{t_2^0}^{t_2^1} \dots \int_{t_2^0}^{t_2^{n-1}} F(t_2, t_2^1) \tilde{B}(t_2^1) \sigma_2(t_2^1) D^{-1}(t_2^1) C(t_2^1) F(t_2^1, t_2^2) \tilde{B}(t_2^2) \sigma_2(t_2^2) D^{-1}(t_2^2) C(t_2^2) \times \\ &\quad F(t_2^2, t_2^3) \dots F(t_2^{n-1}, t_2^n) \tilde{B}(t_2^n) \sigma_2(t_2^n) D^{-1}(t_2^n) C(t_2^n) F(t_2^n, t_2^0) dt_2^n dt_2^{n-1} \dots dt_2^1 - \dots \end{aligned}$$

Proof: Notice that the formula for $F(t_2, t_2^0)$ is just Peano-Baker formula for $F(t_2, t_2^0)$ generalized from the differential equation (holding for the differential vessel)

$$\frac{d}{dt_2} F^\times(t_2, t_2^0) = A_2^\times(t_2) F^\times(t_2, t_2^0) = -[A_2(t_2) - \tilde{B}\sigma_2 D^{-1}(t_2)C(t_2)] F^\times(t_2, t_2^0)$$

□

6.3 Projection, compression and cascade decomposition of systems

Following the construction of cascade connection, it is natural to ask whether the reverse construction exists. One of the main ingredients of this construction is that the state space $\mathcal{H}_{t_2}$ is decomposed into two subspaces $\mathcal{H} = \mathcal{H}'_{t_2} \oplus \mathcal{H}''_{t_2}$, which are invariant for the following operators:

$$\begin{aligned} A_1(t_2)\mathcal{H}'_{t_2} &\subseteq \mathcal{H}'_{t_2}, \quad F(t_2, t_2^0)\mathcal{H}'_{t_2^0} = \mathcal{H}'_{t_2}, \quad \forall t_2, t_2^0 \\ A_1^\times(t_2)\mathcal{H}''_{t_2} &\subseteq \mathcal{H}''_{t_2}, \quad F^\times(t_2, t_2^0)\mathcal{H}''_{t_2^0} = \mathcal{H}''_{t_2}, \quad \forall t_2, t_2^0 \end{aligned}$$

In the differential case this means that $\mathcal{H}'_{t_2}$ is invariant under $A_1(t_2), A_2(t_2)$ for all t_2 and that $\mathcal{H}''_{t_2}$ is invariant under $A_1^\times(t_2), A_2^\times(t_2)$ for all t_2 .

Definition 6.1 *Given a vessel $\mathfrak{V}$ subspaces $\mathcal{G}_{t_2} \subseteq \mathcal{H}_{t_2}$ are called **invariant** if for all t_2 holds*

$$A_1(t_2)\mathcal{G}_{t_2} \subseteq \mathcal{G}_{t_2}, \quad F(t_2, t_2^0)\mathcal{G}_{t_2^0} = \mathcal{G}_{t_2}.$$

*Subspaces $\mathcal{G}_{t_2}^\times \subseteq \mathcal{H}_{t_2}$ are called **co-invariant** if their complements $\mathcal{H}_{t_2} \dot{\ominus} \mathcal{G}_{t_2}^\times$ are invariant and if these subspaces are invariant for the operators $A_1^\times(t_2)$ and $F^\times(t_2, t_2^0)$ (defined in theorem 6.4), i.e., if for all t_2 holds*

$$A_1^\times(t_2)\mathcal{G}_{t_2}^\times \subseteq \mathcal{G}_{t_2}^\times, \quad F^\times(t_2, t_2^0)\mathcal{G}_{t_2^0}^\times = \mathcal{G}_{t_2}^\times.$$

The classical condition for a cascade decomposition and a factorization of the transfer function [BGK, BFKD, S] uses these two notions of invariance. We present an analogue of the corresponding theorems.

Assume that we are given an overdetermined $2D$ system, t_1 invariant (3.1) with the vessel

$$\mathfrak{V} = (A_1(t_2), F(t_2, t_2^0), \tilde{B}(t_2), C(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{H}_{t_2}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*).$$

Suppose also that we are given subspaces $\mathcal{G}_{t_2} \subseteq \mathcal{H}_{t_2}$ that are invariant. Then it is possible to define a *projection* of the vessel $\mathfrak{V}$ onto the invariant subspaces $\mathcal{G}_{t_2}$ as follows

Definition 6.2 *Projection of the vessel $\mathfrak{V}$ on the invariant subspaces $\mathcal{G}_{t_2}$ is a collection*

$$\mathfrak{V}' = (A'_1(t_2), F'(t_2, t_2^0), \tilde{B}'(t_2), C'(t_2), D(t_2), \tilde{D}(t_2); \sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma'_{1*}(t_2), \sigma'_{2*}(t_2)\gamma'_*(t_2); \mathcal{G}_{t_2}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}', \tilde{\mathcal{E}}'_*).$$

where denoting by $P_{\mathcal{G}_{t_2}}$ - projection on $\mathcal{G}_{t_2}$, the operators in $\mathfrak{V}'$ are

$$\begin{aligned} F'(t_2, t_2^0) &= F(t_2, t_2^0)P_{\mathcal{G}(t_2^0)}, \\ A'_1(t_2) &= F'(t_2, t_2^0)A_1(t_2^0)F'(t_2^0, t_2), \\ B'(t_2) &= P_{\mathcal{G}_{t_2}}B(t_2), \\ C'(t_2) &= C(t_2)P_{\mathcal{G}_{t_2}}, \end{aligned}$$

and $\sigma'_{1*}(t_2), \sigma'_{2*}(t_2), \gamma'_*(t_2)$ are taken so that the linkage conditions (2.10.Link) are satisfied

$$\sigma'_{1*}D = \tilde{D}\sigma_1, \quad \sigma'_{2*}D = \tilde{D}\sigma_2, \quad \tilde{D}\gamma = \sigma'_{2*}C'\tilde{B}'\sigma_1 - \sigma'_{1*}C'\tilde{B}'\sigma_2 + \sigma'_{1*}\frac{d}{dt_2}D + \gamma'_*D.$$

Let $\mathcal{G}_{t_2}^\times$ be co-invariant subspaces. Then we define *compression* of the vessel $\mathfrak{V}$ onto the co-invariant subspaces $\mathcal{G}_{t_2}^\times$ as follows

Definition 6.3 *Compression of the vessel $\mathfrak{V}$ on the co-invariant subspaces $\mathcal{G}_{t_2}^\times$ is a collection*

$$\mathfrak{V}^\times = (A_1^\times(t_2), F^\times(t_2, t_2^0), \tilde{B}^\times(t_2), C^\times(t_2), D(t_2), \tilde{D}(t_2); \sigma_1''(t_2), \sigma_2''(t_2), \gamma''(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2)\gamma_*(t_2); \mathcal{G}_{t_2}^\times, \mathcal{E}'', \mathcal{E}_*'', \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*).$$

where $A_1^\times(t_2), F^\times(t_2, t_2^0)$ are defined as in theorem 6.4 and denoting by $P_{\mathcal{G}_{t_2}^\times}^\times$ - projection on $\mathcal{G}_{t_2}^\times$

$$B^\times(t_2) = P_{\mathcal{G}_{t_2}^\times}^\times B(t_2), \quad C''(t_2) = C(t_2)P_{\mathcal{G}_{t_2}^\times}^\times,$$

the operators $\sigma_1''(t_2), \sigma_2''(t_2), \gamma''(t_2)$ are taken so that the linkage conditions (2.10.Link) are satisfied

$$\sigma_{1*}D = \tilde{D}\sigma_1'', \quad \sigma_{2*}D = \tilde{D}\sigma_2'', \quad \tilde{D}\gamma'' = \sigma_{2*}C^\times\tilde{B}^\times\sigma_1'' - \sigma_{1*}C^\times\tilde{B}^\times\sigma_2'' + \sigma_{1*}\frac{d}{dt_2}D + \gamma_*D$$

Lemma 6.5 $\mathfrak{V}', \mathfrak{V}^\times$ are vessels.

Proof: We will show that $\mathfrak{V}'$ is a vessel. For $\mathfrak{V}''$ the proof is essentially the same.

First we show that $F'(s, t)$ is an evolution group. $F'(s, s) = F(s, s)P_{\mathcal{G}(s)} = I_{\mathcal{G}(t_2^0)}$,

$$F'(s, t)F'(t, y) = F(s, t)P_{\mathcal{G}(t)}F(t, y)P_{\mathcal{G}(y)} = F(s, t)F(t, y)P_{\mathcal{G}(y)} = F(s, y)P_{\mathcal{G}(y)} = F'(t, y).$$

Then we have to show that all vessel conditions are satisfied.

$$A'_1(t_2)F'(t_2, t_2^0) = F'(t_2, t_2^0)A_1(t_2^0)F'(t_2, t_2^0)F'(t_2, t_2^0) = F(t_2, t_2^0)A_1(t_2^0)P_{G(t_2^0)} = F'(t_2, t_2^0)A'_1(t_2^0),$$

which means that the Lax equation holds. In order to check the input vessel condition notice that

$$F'(t_2^0, t_2)\tilde{B}'(t_2) = P_{G(t_2^0)}F(t_2^0, t_2)P_{G_{t_2}}\tilde{B}(t_2) = P_{G(t_2^0)}F(t_2^0, t_2)\tilde{B}(t_2),$$

and in the same manner

$$\begin{aligned} F'(t_2^0, t_2)A'_1(t_2)\tilde{B}'(t_2) &= F'(t_2^0, t_2)F'(t_2, t_2^0)A_1(t_2^0)F'(t_2^0, t_2)P_{G_{t_2}}B(t_2) = \\ &= A_1(t_2^0)P_{G(t_2^0)}F(t_2^0, t_2)\tilde{B}(t_2) = P_{G(t_2^0)}F(t_2^0, t_2)A_1(t_2)\tilde{B}(t_2). \end{aligned}$$

So, the input vessel condition is

$$\begin{aligned} \frac{d}{dt_2}(F'(t_2^0, t_2)\tilde{B}'(t_2)\sigma_1(t_2)) + F'(t_2^0, t_2)A'_1(t_2)\tilde{B}'(t_2)\sigma_2(t_2) + F'(t_2^0, t_2)\tilde{B}'(t_2)\gamma(t_2) = \\ = P_{G(t_2^0)}[\frac{d}{dt_2}(F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1(t_2)) + F(t_2^0, t_2)A_1(t_2)\tilde{B}(t_2)\sigma_2(t_2) + F(t_2^0, t_2)\tilde{B}(t_2)\gamma(t_2)] = P_{G(t_2^0)}0 = 0. \end{aligned}$$

The output vessel condition is a consequence of other conditions by considering the differential equation

$$\frac{\partial}{\partial t_2}S'(\lambda, t_2) = \sigma_{1*}^{-1}(t_2)(\lambda\sigma_{2*}(t_2) + \gamma'_*(t_2))S'(\lambda, t_2) - S'(\lambda, t_2)\sigma_1^{-1}(t_2)(\lambda\sigma_2(t_2) + \gamma(t_2))$$

for the projected transfer function

$$\begin{aligned} S'(\lambda, t_2) &= D(t_2) + C'(t_2)(\lambda I - A'_1(t_2))^{-1}\tilde{B}'(t_2)\sigma_1 = \\ &= D(t_2) + C(t_2)F(t_2, t_2^0)P_{t_2^0}(\lambda I - A_1(t_2^0))^{-1}P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1. \end{aligned} \tag{6.5}$$

Let us first evaluate the derivative

$$\begin{aligned} \frac{\partial}{\partial t_2}S'(\lambda, t_2) &= \frac{\partial}{\partial t_2}D + \frac{\partial}{\partial t_2}[C(t_2)F(t_2, t_2^0)P_{t_2^0}](\lambda I - A_1(t_2^0))^{-1}P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1 + \\ &\quad + C(t_2)F(t_2, t_2^0)P_{t_2^0}(\lambda I - A_1(t_2^0))^{-1}P_{t_2^0}\frac{\partial}{\partial t_2}[F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1] = \\ &= \frac{\partial}{\partial t_2}D + \sigma_{1*}^{-1}[\sigma_{2*}C(t_2)F(t_2, t_2^0)A_1(t_2^0)P_{t_2^0} + \gamma'C(t_2)F(t_2, t_2^0)P_{t_2^0}](\lambda I - A_1(t_2^0))^{-1}P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1 - \\ &\quad - C(t_2)F(t_2, t_2^0)P_{t_2^0}(\lambda I - A_1(t_2^0))^{-1}P_{t_2^0}[A_1(t_2^0)F(t_2^0, t_2)\tilde{B}(t_2)\sigma_2 + F(t_2^0, t_2)\tilde{B}(t_2)\gamma] = \\ &= \frac{\partial}{\partial t_2}D + \sigma_{1*}^{-1}[\sigma_{2*}\lambda + \gamma']C(t_2)F(t_2, t_2^0)P_{t_2^0}(\lambda I - A_1(t_2^0))^{-1}P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1 - \\ &\quad - C(t_2)F(t_2, t_2^0)P_{t_2^0}(\lambda I - A_1(t_2^0))^{-1}P_{t_2^0}A_1(t_2^0)F(t_2^0, t_2)\tilde{B}(t_2)[\lambda\sigma_2 + \gamma] - \\ &\quad - \sigma_{1*}^{-1}\sigma_{2*}C(t_2)F(t_2, t_2^0)P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1 + C(t_2)F(t_2, t_2^0)P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_2 = \\ &= \frac{\partial}{\partial t_2}D + \sigma_{1*}^{-1}[\sigma_{2*}\lambda + \gamma'](-D + S'(\lambda, t_2)) - (-D + S'(\lambda, t_2))\sigma_1^{-1}[\lambda\sigma_2 + \gamma] - \\ &\quad - \sigma_{1*}^{-1}\sigma_{2*}C(t_2)F(t_2, t_2^0)P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_1 + C(t_2)F(t_2, t_2^0)P_{t_2^0}F(t_2^0, t_2)\tilde{B}(t_2)\sigma_2 = \\ &= \frac{\partial}{\partial t_2}D + \sigma_{1*}^{-1}[\sigma_{2*}\lambda + \gamma'](-D + S'(\lambda, t_2)) - (-D + S'(\lambda, t_2))\sigma_1^{-1}[\lambda\sigma_2 + \gamma] - \\ &\quad - \sigma_{1*}^{-1}\sigma_{2*}C'(t_2)P_{t_2^0}\tilde{B}'(t_2)\sigma_1 + C'(t_2)P_{t_2^0}\tilde{B}'(t_2)\sigma_2. \end{aligned}$$

If we plug this expression into (6.5), we shall obtain

$$\begin{aligned} \frac{\partial}{\partial t_2}D - \sigma_{1*}^{-1}[\sigma_{2*}\lambda + \gamma']D + D\sigma_1^{-1}[\lambda\sigma_2 + \gamma] - \\ - \sigma_{1*}^{-1}\sigma_{2*}C'(t_2)P_{t_2^0}\tilde{B}'(t_2)\sigma_1 + C'(t_2)P_{t_2^0}\tilde{B}'(t_2)\sigma_2 = 0 \end{aligned}$$

□

It is also possible to perform a compression of the vessel on a semi-invariant subspace. Let us first define it. Suppose that $\mathcal{G}_{t_2}$ is an invariant subspace of the vessel $\mathfrak{V}$. Suppose also that there is a co-invariant within $\mathcal{G}_{t_2}$ subspace $\mathcal{G}'_{t_2} \subseteq \mathcal{G}_{t_2}$, that is the subspace $\mathcal{G}_{t_2} \setminus \mathcal{G}'_{t_2}$ is co-invariant. In this case we call $\mathcal{G}'_{t_2}$ a *semi-invariant* subspace of $\mathfrak{V}$. Then performing projection of the vessel $\mathfrak{V}$ on the invariant subspace $\mathcal{G}_{t_2}$, we shall obtain a new vessel $\mathfrak{V}'$. Performing further compression on the co-invariant subspace $\mathcal{G}'_{t_2}$ we shall obtain the desired vessel $\mathfrak{V}''$.

Remarks: 1. Notice that invertibility of $D(t_2)$ is not essential but suffices in order to determine all the relevant data. For example, in the case of projection on an invariant space $\mathcal{G}_{t_2}$ one obtains

$$\sigma'_{1*} = \tilde{D}\sigma_1 D^{-1}, \quad \sigma'_{2*} = \tilde{D}\sigma_2 D^{-1}, \quad \gamma'_* = \tilde{D}\gamma D^{-1} - [\sigma'_{2*} C' \tilde{B}' \sigma_1 - \sigma'_{1*} C' \tilde{B}' \sigma_2 + \sigma'_{1*} \frac{d}{dt_2} D] D^{-1}$$

and consequently they are uniquely determined.

2. It is enough to have a subspace $\mathcal{G}_{t_2^0} \subseteq \mathcal{H}_{t_2^0}$ that is invariant under $A_1(t_2^0)$ with a complementary subspace $\mathcal{G}_{t_2^0}^\times \subseteq \mathcal{H}_{t_2^0}$ that is invariant under $A_1^\times(t_2^0)$ and such that

$$F(t_2, t_2^0) \mathcal{G}_{t_2^0}, \quad F(t_2, t_2^0) \mathcal{G}_{t_2^0}^\times$$

are complementary for all t_2 .

3. For the conservative case (to be studied later) $A_1^\times(t_2) = A_1^*(t_2)$, so the existence of a complementary invariant subspace is automatic, just like in the classical case.

As a result of all these consideration we deduce a theorem of cascade decomposition of vessels. Suppose that we are given an invariant subspace $\mathcal{G}_{t_2}$, which is at the same time co-invariant. Then it is possible to produce a projection on $\mathcal{G}_{t_2}$ and compression on its complement. The point is that the obtained in such a way vessel can be cascade connected to give the initial one. This is precisely the content of the next theorem

Theorem 6.6 *Suppose that we are given a vessel $\mathfrak{V}$ of the form (6.3) with invariant subspace $\mathcal{G}_{t_2}$, and co-invariant subspace $\mathcal{G}_{t_2}^\times$, then the projection on $\mathcal{G}_{t_2}$ produces a vessel $\mathfrak{V}'$ and compression to $\mathcal{G}_{t_2}^\times$ produces $\mathfrak{V}^\times$. Moreover, it is possible to cascady connect these two vessels and to obtain the original one $\mathfrak{V}$.*

7 Kalman decomposition of Vessels

The notions of approximate controllability and observability allows building of minimal systems for which there is a very good classification theory. It turns out that there are possible other parts of a system (vessel) that are non-approximately controllable or are not observable. Let us denote the system (3.1) (for fixed $\sigma_1(t_2), \sigma_2(t_2), \gamma(t_2), \sigma_{1*}(t_2), \sigma_{2*}(t_2), \gamma_*(t_2)$)

$$I\Sigma : \begin{cases} \frac{\partial}{\partial t_1} x(t_1, t_2) = A_1(t_2) x(t_1, t_2) + \tilde{B}(t_2) \sigma_1(t_2) u(t_1, t_2) \\ x(t_1, t_2) = F(t_2, t_2^0) x(t_1, t_2^0) + \int_{t_2^0}^{t_2} F(t_2, s) \tilde{B}(s) \sigma_2(s) u(t_1, s) ds \\ y(t_1, t_2) = C(t_2) x(t_1, t_2) + D(t_2) u(t_1, t_2). \end{cases}$$

by

$$I\Sigma = [A_1(t_2), F(t_2, t_2^0), \tilde{B}(t_2), C(t_2), D(t_2)].$$

Theorem 7.1 Let $I\Sigma$ be a system defined in (3.1) with inner state space $\mathcal{H}_{t_2}$ for each t_2 . Then there exists an orthogonal (for each t_2) decomposition of the state space

$$\mathcal{H}_{t_2} = \mathcal{H}_{t_2}^{c\bar{o}} \oplus \mathcal{H}_{t_2}^{co} \oplus \mathcal{H}_{t_2}^{\bar{c}o} \oplus \mathcal{H}_{t_2}^{\bar{c}\bar{o}}$$

so that with respect to this decomposition the system has the following decomposition of its operators

$$\begin{aligned} A_1(t_2) &= \begin{bmatrix} A_1^{c\bar{o}}(t_2) & A_{12}(t_2) & A_{13}(t_2) & A_{14}(t_2) \\ 0 & A_1^{co}(t_2) & A_{23}(t_2) & A_{24}(t_2) \\ 0 & 0 & A_1^{\bar{c}o}(t_2) & A_{34}(t_2) \\ 0 & 0 & 0 & A_1^{\bar{c}\bar{o}}(t_2) \end{bmatrix}; \\ \tilde{B}(t_2) &= \begin{bmatrix} \tilde{B}^{c\bar{o}} \\ \tilde{B}^{co} \\ 0 \\ 0 \end{bmatrix} \\ C(t_2) &= \begin{bmatrix} 0 & C^{co}(t_2) & 0 & C^{\bar{c}o}(t_2) \end{bmatrix} \\ F(t_2, t_2^0) &= \begin{bmatrix} F^{c\bar{o}}(t_2, t_2^0) \\ F^{co}(t_2, t_2^0) \\ F^{\bar{c}o}(t_2, t_2^0) \\ F^{\bar{c}\bar{o}}(t_2, t_2^0) \end{bmatrix} \end{aligned}$$

where the subsystem, defined by

$$I\Sigma^c = \left[\begin{bmatrix} A_1^{c\bar{o}}(t_2) & A_{12}(t_2) \\ 0 & A_1^{co}(t_2) \end{bmatrix}, \begin{bmatrix} F^{c\bar{o}}(t_2, t_2^0) \\ F^{co}(t_2, t_2^0) \end{bmatrix}, \begin{bmatrix} \tilde{B}^{c\bar{o}} \\ \tilde{B}^{co} \end{bmatrix}, \begin{bmatrix} 0 & C^{co}(t_2) \end{bmatrix}, D \right]$$

is approximately controllable, the system

$$I\Sigma^o = \left[\begin{bmatrix} A_1^{co}(t_2) & A_{24}(t_2) \\ 0 & A_1^{\bar{c}o}(t_2) \end{bmatrix}, \begin{bmatrix} F^{co}(t_2, t_2^0) \\ F^{\bar{c}o}(t_2, t_2^0) \end{bmatrix}, \begin{bmatrix} \tilde{B}^{co} \\ 0 \end{bmatrix}, \begin{bmatrix} C^{co}(t_2) & C^{\bar{c}o}(t_2) \end{bmatrix}, D \right]$$

is observable, and the system

$$I\Sigma^{co} = [A_1^{co}, F^{co}(t_2, t_2^0), \tilde{B}^{co}(t_2), C^{co}(t_2), D]$$

is minimal (i.e., approximately controllable and observable). Moreover, the transfer functions of all the systems are equal:

$$S(\lambda, t_2) = S^c(\lambda, t_2) = S^o(\lambda, t_2) = S^{co}(\lambda, t_2).$$

Proof: Denote for each t_2

$$\begin{aligned} \mathcal{G}_c(t_2) &= \overline{\text{span}}\{\text{Im } A_1^j(t_2)B(t_2) \mid j = 0, 1, 2, \dots\}, & \mathcal{G}_{\bar{c}}(t_2) &= \mathcal{H}_{t_2} \ominus \mathcal{G}_c(t_2) \\ \mathcal{G}_o(t_2) &= \overline{\text{span}}\{\text{Im } A_1^{*j}(t_2)C^*(t_2) \mid j = 0, 1, 2, \dots\}, & \mathcal{G}_{\bar{o}}(t_2) &= \mathcal{H}_{t_2} \ominus \mathcal{G}_o(t_2) \end{aligned}$$

Now write each operator in the system $I\Sigma$ as an operator with respect to $\mathcal{G}_c(t_2)$ and $\mathcal{G}_{\bar{c}}(t_2)$. Since $\mathcal{G}_c(t_2)$ is $A_1(t_2)$ invariant, the system $I\Sigma = [A_1(t_2), F(t_2, t_2^0), \tilde{B}(t_2), C(t_2), D(t_2)]$ is of the following form

$$\left[\begin{bmatrix} A_1^c(t_2) & A_{12}(t_2) \\ 0 & A_1^{\bar{c}}(t_2) \end{bmatrix}, \begin{bmatrix} F^c(t_2, t_2^0) \\ F^{\bar{c}}(t_2, t_2^0) \end{bmatrix}, \begin{bmatrix} \tilde{B}^c(t_2) \\ \tilde{B}^{\bar{c}}(t_2) \end{bmatrix}, \begin{bmatrix} C^c(t_2) & C^{\bar{c}}(t_2) \end{bmatrix}, D(t_2) \right]$$

and clearly

$$C^c(t_2)A^c(t_2)B^c(t_2) = C(t_2)A(t_2)B(t_2).$$

Thus the original system $I\Sigma$ has the same transfer function as

$$I\Sigma^c = [A_1^c(t_2), F^c(t_2, t_2^0), \tilde{B}^c(t_2), C^c(t_2), D(t_2)]$$

and this system is approximately controllable. The same process works on the given system (3.1) with observability ($\mathcal{G}_o$ rather than $\mathcal{G}_o$ is invariant under $A_1(t_2)$) to give a "smaller" observable system

$$I\Sigma^o = [A_1^o(t_2), F^o(t_2, t_2^0), \tilde{B}^o(t_2), C^o(t_2), D(t_2)].$$

If one combines these two processes, one gets (by first decomposing the system $I\Sigma$ into controllable and uncontrollable parts and then decomposing these systems into observable and unobservable parts) the desired decomposition. $\square$

8 Analytic functions as transfer functions

The aim of this section is to show that any function in our class $\mathcal{I}$ can be realized, i.e., presented as a transfer function of a certain vessel.

8.1 Realization theorem for arbitrary analytic functions in $\mathcal{I}$

So, suppose that we are given a function $S(\lambda, t_2) \in \mathcal{I}$. Our first aim is to realize this function, i.e. to show that this class is realizable. In order to do it, we realize $S(\lambda, t_2)$ for a fixed t_2^0 [H] as

$$S(\lambda, t_2^0) = D_0 + C_0(\lambda I - A_1)^{-1}B_0\sigma_1(t_2^0).$$

Then the following theorem holds

Theorem 8.1 *Suppose that $S(\lambda, t_2) \in \mathcal{I}$. Then there exists vessel $\mathfrak{DV}$ in the differential form*

$$\mathfrak{DV} = (A_1(t_2), A_2(t_2), B(t_2), C(t_2), D(t_2), \tilde{D}; \sigma_1, \sigma_2, \gamma, \sigma_{1*}, \sigma_{2*}, \gamma_*; \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*),$$

with this transfer function and for which

$$C(t_2) = \oint_{\text{Spec} A_1} \Phi_*(\lambda, t_2, t_2^0) C_0(\lambda I - A_1)^{-1} d\lambda \quad (8.1)$$

$$B(t_2) = \oint_{\text{Spec} A_1} (\lambda I - A_1)^{-1} B_0 \sigma_1(t_2) \Phi^*(-\bar{\lambda}, t_2, t_2^0) d\lambda \quad (8.2)$$

$$D(t_2) = S(\infty, t_2) \quad (8.3)$$

and

$$S(\lambda, t_2) = D(t_2) + C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1.$$

Before we consider the proof of this theorem, it is important to note that for the functions $C(t_2), B(t_2)$ the following lemma holds

Lemma 8.2 $C(t_2), B(t_2)$ satisfy the following differential equations with the spectral operator parameter A_1 :

$$\begin{aligned}\frac{d}{dt_2}C(t_2) &= \sigma_{1*}^{-1}(t_2)[\sigma_{2*}(t_2)C(t_2)A_1 + \gamma_*(t_2)C(t_2)] \\ \frac{d}{dt_2}[B(t_2)\sigma_1(t_2)] &= A_1B(t_2)\sigma_2(t_2) + B(t_2)\gamma(t_2)\end{aligned}$$

Proof: For $C(t_2)$ one obtains that

$$\begin{aligned}\sigma_1 C(t_2)' &= \sigma_1 \frac{\partial}{\partial t_2} \oint_{\text{Spec} A_1} \Phi_*(\lambda, t_2, t_2^0) C_0(\lambda I - A_1)^{-1} d\lambda = \\ &= \sigma_1 \oint_{\text{Spec} A_1} \sigma_1^{-1}(\sigma_2 \lambda + \gamma_*) \Phi_*(\lambda, t_2, t_2^0) C_0(\lambda I - A_1)^{-1} d\lambda = \\ &= \oint_{\text{Spec} A_1} \sigma_2 \Phi_*(\lambda, t_2, t_2^0) C_0(\lambda I - A_1 + A_1)(\lambda I - A_1)^{-1} d\lambda + \\ &\quad + \oint_{\text{Spec} A_1} \gamma_* \Phi_*(\lambda, t_2, t_2^0) C_0(\lambda I - A_1)^{-1} d\lambda = \\ &= \sigma_2 \oint_{\text{Spec} A_1} \Phi_*(\lambda, t_2, t_2^0) C_0(\lambda I - A_1)^{-1} d\lambda A_1 + \gamma_* \oint_{\text{Spec} A_1} \Phi_*(\lambda, t_2, t_2^0) C_0(\lambda I - A_1)^{-1} d\lambda = \\ &= \sigma_2 C(t_2) A_1 + \gamma_* C(t_2)\end{aligned}$$

and the same proof works for $B(t_2)$. □

Proof of theorem 8.1: Let us define a vessel:

$$\mathfrak{DV} = (A_1, A_2 = 0, B(t_2), C(t_2), D(t_2), \tilde{D} = \sigma_{1*} D(t_2) \sigma_1^{-1}, \sigma_1, \sigma_2, \gamma, \sigma_{1*}, \sigma_{2*}, \gamma_*, \mathcal{H}, \mathcal{E}, \mathcal{E}_*, \tilde{\mathcal{E}}, \tilde{\mathcal{E}}_*),$$

and show that all vessel conditions hold. Lax equation holds

$$\frac{d}{dt_2} A_1 = 0 = A_1 A_2 - A_2 A_1 = A_1 0 - 0 A_1.$$

The first (2.5.OverD) and the second (2.9.OverD) vessel conditions are exactly the contents of lemma 8.2.

Consider next the expression $C(t_2)(\lambda I - A_1)^{-1} B(t_2) \sigma_1(t_2)$. Using lemma (8.2) we obtain that

$$\begin{aligned}&\frac{\partial}{\partial t_2} (C(t_2)(\lambda I - A_1)^{-1} B(t_2) \sigma_1(t_2)) = \\ &\sigma_{1*}^{-1}(\sigma_{2*} C(t_2) A_1 + \gamma_*(t_2) C(t_2)) (\lambda I - A_1)^{-1} B(t_2) \sigma_1(t_2) + \\ &\quad + C(t_2)(\lambda I - A_1)^{-1} [A_1 B(t_2) \sigma_2(t_2) + B(t_2) \gamma(t_2)] = \\ &= \sigma_{1*}^{-1}(\sigma_{2*} \lambda + \gamma_*(t_2)) C(t_2)(\lambda I - A_1)^{-1} B(t_2) \sigma_1(t_2) - C(t_2)(\lambda I - A_1)^{-1} B(t_2) (\sigma_2(t_2) \lambda + \gamma(t_2)) - \\ &\quad - \sigma_{1*}^{-1} \sigma_{2*} C(t_2) B(t_2) \sigma_1(t_2) + C(t_2) B(t_2) \sigma_1(t_2) \sigma_1^{-1}(t_2) \sigma_2(t_2)\end{aligned}$$

We can use here the fundamental matrices $\Phi(\lambda, t_2, t_2^0)$, $\Phi_*(\lambda, t_2, t_2^0)$ and with the help of variation of coefficients, we obtain that

$$C(t_2)(\lambda I - A_1)^{-1} B(t_2) \sigma_1(t_2) = \Phi_*(\lambda, t_2, t_2^0) K(\lambda, t_2) \Phi^{-1}(\lambda, t_2, t_2^0),$$

where

$$\begin{aligned}&\frac{\partial}{\partial t_2} K(\lambda, t_2) = \\ &\Phi_*^{-1}(\lambda, t_2, t_2^0) (-\sigma_{1*}^{-1} \sigma_{2*} C(t_2) B(t_2) \sigma_1(t_2) + C(t_2) B(t_2) \sigma_1(t_2) \sigma_1^{-1}(t_2) \sigma_2(t_2)) \Phi(\lambda, t_2, t_2^0)\end{aligned}$$

with the initial value $K(\lambda, t_2^0) = C(t_2^0)(\lambda I - A_1)^{-1}B(t_2^0)\sigma_1(t_2^0)$. Since the fundamental matrices are entire in λ functions, we also obtain that

$$K(\lambda, t_2) - K(\lambda, t_2^0) = \int_{t_2^0}^{t_2} \frac{\partial}{\partial y} K(\lambda, y) dy$$

is an entire function of λ . Thus

$$\begin{aligned} S(\lambda, t_2) - C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1(t_2) &= \Phi_*(\lambda, t_2, t_2^0)(S(\lambda, t_2^0) - K(\lambda, t_2))\Phi^{-1}(\lambda, t_2, t_2^0) = \\ &= \Phi_*(\lambda, t_2, t_2^0)(D(t_2^0) + C(t_2^0)(\lambda I - A_1)^{-1}B(t_2^0)\sigma_1(t_2^0) - \\ &\quad - C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1(t_2) - \int_{t_2^0}^{t_2} \frac{\partial}{\partial y} K(\lambda, y) dy)\Phi^{-1}(\lambda, t_2, t_2^0) = \\ &= \Phi_*(\lambda, t_2, t_2^0)(D(t_2^0) + \frac{\partial}{\partial y} K(\lambda, y) dy)\Phi^{-1}(\lambda, t_2, t_2^0), \end{aligned}$$

which is an entire in λ function too. On the other hand, when λ tends to ∞ , $S(\infty, t_2) = D(t_2)$ and $\lim_{\lambda \rightarrow \infty} C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1(t_2) = 0$, which means that their difference is bounded and consequently, by Liouville's theorem for operator valued functions, applied to constant vectors is constant. Finally,

$$S(\lambda, t_2) = D(t_2) + C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1(t_2). \quad (8.4)$$

Once we have established all these formulas, it remains to show that the linkage conditions (2.10.Link)

$$\begin{aligned} \sigma_{1*}D &= \tilde{D}\sigma_1, \quad \sigma_{2*}D = \tilde{D}\sigma_2 \\ \tilde{D}\gamma &= \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}C\tilde{B}\sigma_2 - \sigma_{1*}\frac{d}{dt_2}D + \gamma_*D \end{aligned}$$

are satisfied. In order to do this, we use the differential equation for $S(\lambda, t_2)$ (3.11)

$$\frac{\partial}{\partial t_2} S(\lambda, t_2) = \sigma_1^{-1}(t_2)(\sigma_{2*}(t_2)\lambda + \gamma_*(t_2))S(\lambda, t_2) - S(\lambda, t_2)\sigma_1^{-1}(t_2)(\sigma_2(t_2)\lambda + \gamma(t_2)).$$

and substitute here the realization formula (8.4). Then

$$\begin{aligned} \frac{d}{dt_2} D(t_2) + \frac{d}{dt_2} C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1(t_2) + C(t_2)(\lambda I - A_1)^{-1} \frac{d}{dt_2} (B(t_2)\sigma_1(t_2)) = \\ = \sigma_1^{-1}(t_2)(\sigma_{2*}(t_2)\lambda + \gamma_*(t_2))(D(t_2) + C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1(t_2)) - \\ - (D(t_2) + C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1(t_2))\sigma_1^{-1}(t_2)(\sigma_2(t_2)\lambda + \gamma(t_2)). \end{aligned}$$

Considering the linear in λ part, for big values of λ we immediately obtain that

$$\sigma_{1*}^{-1}\sigma_{2*}D = D\sigma_1^{-1}\sigma_2,$$

and plugging this back into the differential equation, and tending λ to infinity, we obtain (defining $\tilde{D} = \sigma_{1*}D\sigma_1^{-1}$) that

$$\tilde{D}\gamma = \sigma_{2*}C\tilde{B}\sigma_1 - \sigma_{1*}C\tilde{B}\sigma_2 - \sigma_{1*}\frac{d}{dt_2}D + \gamma_*D,$$

which finishes the proof. $\square$

Notice that there are no assumptions on the dimensions of $\mathcal{E}, \mathcal{E}_*$. In the next section we consider the finite dimensional case $\dim \mathcal{H}_{t_2} < \infty$.

8.2 Realization theorem for matrix functions in $\mathcal{I}$

In this section we want to further investigate the formulas for $C(t_2), B(t_2)$ arising in the realization of $S(\lambda, t_2) \in K$ for the matrix case. So, $S(\lambda, t_2)$ maps solutions of the input ODE (3.7) with the spectral parameter λ to solutions of the output ODE (3.8) with the same spectral parameter. By Jordan theorem any constant matrix is similar to its unique Jordan form, and consequently, we are going to concentrate on this special case. More explicit realization, based on the theorem 8.1 is achieved in the next theorem.

So, suppose that there is only one eigenvalue for A_1 of multiplicity n ,

Theorem 8.3 *Suppose that $S(\lambda, t_2)$ has one pole z of maximal order n . Then there exists a chain of functions $\{c_{0*}, c_{1*}, \dots, c_{n*}\}$ and $\{b_0, b_1, \dots, b_n\}$ such that*

$$S(\lambda, t_2) = D + \begin{bmatrix} c_{0*} & c_{1*} & \dots & c_{(n-1)*} \end{bmatrix} (\lambda I - \text{Jordan}(z))^{-1} \begin{bmatrix} b_0^* \\ b_1^* \\ \vdots \\ b_{n-1}^* \end{bmatrix} \sigma_1$$

1. where c_{0*} is a solution of the output differential equation (3.8) with the spectral parameter z , and c_{i*} is a solution of the differential equation

$$z\sigma_{2*}y - \sigma_{1*}\frac{\partial}{\partial t_2}y + \gamma_*y = \sigma_{2*}c_{i-1*}.$$

2. and b_0 is a solution of the adjoint output differential equation (5.4) with the spectral parameter $-z^*$, and b_i is a solution of the differential equation

$$-z^*\sigma_{2*}y - \sigma_{1*}\frac{\partial}{\partial t_2}y + \gamma y = \sigma_{2*}b_{i-1}.$$

Proof: Remember that $S(\lambda, t_2)$ is of the form (3.10)

$$S(\lambda, t_2) = \Phi_*(\lambda, t_2^0, t_2)S(\lambda, t_2^0)\Phi^{-1}(\lambda, t_2^0, t_2),$$

where $\Phi(\lambda, t_2^0, t_2), \Phi_*(\lambda, t_2^0, t_2)$ are fundamental matrices for the input and the output ODEs, respectively, and $S(\lambda, t_2^0)$ is a rational in λ matrix, for which we can apply the realization theorem:

$$S(\lambda, t_2^0) = D + C(\lambda I - \text{Jordan}[z])^{-1}B$$

Then we have

$$\begin{aligned} S(\lambda, t_2^0, t_2) &= \Phi_*(\lambda, t_2^0, t_2)S(\lambda_0, t_2^0)\Phi^{-1}(\lambda, t_2^0, t_2) \\ &= \Phi_*(\lambda, t_2^0, t_2) \left[D + C \begin{bmatrix} \frac{1}{\lambda-z} & \frac{1}{(\lambda-z)^2} & \frac{1}{(\lambda-z)^3} & \dots & \frac{1}{(\lambda-z)^n} \\ 0 & \frac{1}{\lambda-z} & \frac{1}{(\lambda-z)^2} & \dots & \frac{1}{(\lambda-z)^{n-1}} \\ 0 & 0 & \frac{1}{\lambda-z} & \dots & \frac{1}{(\lambda-z)^{n-2}} \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & \dots & \frac{1}{\lambda-z} \end{bmatrix} B \right] \Phi^{-1}(\lambda, t_2^0, t_2). \end{aligned}$$

Writing now the fundamental matrices in the Taylour series we obtain that

$$\begin{aligned}\Phi_*(\lambda, t_2^0, t_2) &= \Phi_*(z, t_2^0, t_2) + \sum_{k=1}^{\infty} \Phi_{k*}(t_2^0, t_2)(\lambda - z)^k = \sum_{k=0}^{\infty} \Phi_{i*}(\lambda - z)^k, \\ \Phi^{-1}(\lambda, t_2^0, t_2) &= \Phi^{-1}(z, t_2^0, t_2) + \sum_{k'=1}^{\infty} \Phi_{k'}(t_2^0, t_2)(\lambda - z)^{k'} = \sum_{k'=0}^{\infty} \Phi_{k'}(\lambda - z)^{k'}\end{aligned}$$

Inserting these expressions for the fundamental matrices, we are able to calculate the Lourent coefficients explicitly:

1. The coefficient of $\frac{1}{(\lambda - z)^n}$ is

$$\Phi_{0*}Ce_1e_n^*B\Phi_0 = c_{0*}b_0^*\sigma_1,$$

where we denoted $c_{0*} = \Phi_{0*}Ce_1$, $b_0 = \sigma_1^{-1}\Phi_0Be_n$.

2. The coefficient of $\frac{1}{(\lambda - z)^{n-1}}$ is

$$\begin{aligned}\Phi_{0*}Ce_1e_{n-1}^*B\Phi_0 + \Phi_{0*}Ce_2e_n^*B\Phi_0 + \Phi_{0*}Ce_1e_n^*B\Phi_1 + \Phi_{1*}Ce_1e_nB\Phi_0 &= \\ = c_{0*}e_{n-1}^*B\Phi_0 + \Phi_{0*}Ce_2b_0^*\sigma_1 + c_{0*}e_n^*B\Phi_1 + \Phi_{1*}Ce_1b_0^*\sigma_1 &= \\ = c_{0*}[e_{n-1}^*B\Phi_0 + e_n^*B\Phi_1] + [\Phi_{0*}Ce_2 + \Phi_{1*}Ce_1]b_0^*\sigma_1 &= \\ = c_{0*}b_1^*\sigma_1 + c_{1*}b_0^*\sigma_1\end{aligned}$$

Notice that direct calculations show that c_{1*}, b_1 are companion solutions of c_{0*}, b_0 , respectively.

3. The coefficient of $\frac{1}{(\lambda - z)^{n-2}}$ is

$$\begin{aligned}\Phi_{0*}Ce_1(e_{n-2}^*B\Phi_0 + e_{n-1}^*B\Phi_1 + e_nB\Phi_2) + (\Phi_{0*}Ce_2 + \Phi_{1*}Ce_1)(e_{n-1}^*B\Phi_0 + e_n^*B\Phi_1) + \\ (\Phi_{0*}Ce_3 + \Phi_{1*}Ce_2 + \Phi_{2*}Ce_1)e_nB\Phi_0 &= \\ = c_{0*}b_2^*\sigma_1 + c_{1*}b_1^*\sigma_1 + c_{2*}b_0^*\sigma_1,\end{aligned}$$

where we denote $b_2^*\sigma_1 = e_{n-2}^*B\Phi_0 + e_{n-1}^*B\Phi_1 + e_nB\Phi_2$ and $c_{2*} = \Phi_{0*}Ce_3 + \Phi_{1*}Ce_2 + \Phi_{2*}Ce_1$. Again, as in the previous case, it is a matter of simple calculations to show that c_{2*}, b_2 are companion solutions to c_{1*}, b_1 , respectively.

4. For all the other coefficients, by induction, we obtain the desired result.

Notice that $\Phi_{k*}(t_2^0, t_2) = \frac{\partial}{\partial \lambda^k} \Phi_*(\lambda, t_2^0, t_2)|_{\lambda=z}$, $\Phi_k(t_2^0, t_2) = \frac{\partial}{\partial \lambda^k} \Phi^{-1}(\lambda, t_2^0, t_2)|_{\lambda=z}$ and this is used to show the connection between c_{k*} and $c_{(k+1)*}$ (b_k and b_{k+1}). $\square$

It means that one obtains a vessel with the transfer function $S(\lambda, t_2)$ by means of the following definitions:

$$A_1 = \text{Jordan}(z_i), \quad A_2(t_2) = 0, \quad C(t_2) = \text{Col}\{c_{i*}(t_2)\}, \quad B(t_2) = \text{Row}\{b_i(t_2)\}$$

It is a matter of simple calculations to show that all the vessel conditions are satisfied.

As for the general case, suppose that $A_1 = U\Omega U^{-1}$, where Ω is the Jordan block form of A_1 . Then from realization theorem 8.1, we obtain that

$$S(\lambda, t_2) = D(t_2) + C(t_2)(\lambda I - A_1)^{-1}B(t_2)\sigma_1 = D(t_2) + C(t_2)V^{-1}(\lambda I - \Omega)^{-1}VB(t_2)\sigma_1$$

and one can consider the case where A_1 is of the Jordan block form. Suppose that we are given chains of the appropriate sizes of companion solutions $c_{0*}^i, \dots, c_{(n_i-1)*}^i$ and $b_{0*}^i, \dots, b_{(n_i-1)*}^i$ for the output and the adjoint input ODE with the spectral parameter λ_i . Suppose that it is given for each eigenvalue λ_i of Ω . Then the final vessel is obtained by defining $C(t_2)$ as a block matrix, where the matrices $c_{0*}^i \dots c_{(n_i-1)*}^i$ are on the diagonal. The same construction works for $B(t_2)$, so that the final result and vessel conditions are easily verified.

The construction of the system parameters from the residues of the given rational matrix function (which one assumes has only simple poles), is known as the Gilbert realization (see [K], page 349).

It is also appropriate to emphasize here that we have built in theorem 8.3 right and left pole pairs for the matrix function $S(\lambda, t_2)$. Let us recall first the definitions (from [BGR]). From the formula (3.10)

$$S(\lambda, t_2) = \Phi_*(\lambda, t_2, \tau_2) S(\lambda, t_2^0) \Phi^{-1}(\lambda, t_2, t_2^0)$$

it follows that the poles of the matrix $S(\lambda, t_2)$ are independent of t_2 . So, suppose that z is a pole of $S(\lambda, t_2)$, which has the following Laurent expansion around z :

$$S(\lambda, t_2) = \sum_{j=-q}^{\infty} (\lambda - z)^j S_j(t_2).$$

Then $y_0(t_2), \dots, y_{r-1}(t_2)$ is called a *right pole chain* for $S(\lambda, t_2)$ at z , if there exist additional vectors $y_r(t_2), \dots, y_{r+q-1}(t_2)$ (q being the order of z as a pole of $S^{-1}(\lambda, t_2)$) such that $S^{-1}(\lambda, t_2)y(\lambda, t_2)$ is analytic at z with zero of order r at z , where

$$y(\lambda, t_2) = \sum_{j=0}^{r_q-1} (\lambda - z)^j y_j.$$

The natural number r corresponds to a size of Jordan block (with z on the diagonal) to be constructed shortly.

A *canonical right pole pair* $(A_1, B(t_2))$ is a collection of chains

$$B(t_2) = y_0^{(1)}(t_2), \dots, y_{r-1}^{(1)}(t_2); y_0^{(2)}(t_2), \dots, y_{r-1}^{(2)}(t_2); \dots; y_0^{(p)}(t_2), \dots, y_{r-1}^{(p)}(t_2);$$

and corresponding Jordan blocks

$$A_1 = J_1 \oplus J_2 \oplus \dots \oplus J_p.$$

with the property above. Moreover, any pair similar to $(A_1, B(t_2))$, i.e., for an invertible matrix $M(t_2)$, of the form $(M(t_2)A_1M^{-1}(t_2), M(t_2)B(t_2))$ is called a *right pole pair*. Analogously, one defines a *canonical left pole pair* $(C(t_2), A_1)$, when $y(\lambda, t_2)S^{-1}(\lambda, t_2)$ is demanded to be analytic at z with zero of order r at z .

In theorem 8.3 we have constructed such pairs for each t_2 , but even more, the left pole pair $(C(t_2), A_1)$ has an additional property, that $C(t_2)$ satisfies the differential equation in lemma 8.2 with the spectral matrix parameter A_1 . This in turn means that the left pole chains consist of companion solutions of the output ODE (3.8) for poles of $S(\lambda, t_2)$ as described in theorem 8.3. A similar conclusion is true for $(A_1, B(t_2))$.

Finally, a triple $(C(z, t_2), A_1(z), B(z, t_2)\sigma_1(t_2))$ is called a *pole triple at z* of a rational matrix function $S(\lambda, t_2)$ if $(C(z, t_2), A_1(z))$, $(A_1(z), B(z, t_2)\sigma_1(t_2))$ are the left and the right pole pairs at z , respectively. In this case

$$S(\lambda, t_2) - C(z, t_2)(zI - A_1(z))^{-1}B(z, t_2)\sigma_1(t_2)$$

is an analytic function at z . A (full) *pole triple* of $S(\lambda, t_2)$ is just a direct sum of all local pole triples, which respects the order of their appearance:

$$\begin{aligned} C(t_2) &= C(z_1, t_2) \oplus C(z_2, t_2) \oplus \cdots \oplus C(z_p, t_2), \\ A_1 &= \text{diag}\{A_1(z_1), A_1(z_2), \dots, A_1(z_p)\}, \\ B(t_2)\sigma_1(t_2) &= \begin{bmatrix} B(z_1, t_2) \\ B(z_2, t_2) \\ \vdots \\ B(z_p, t_2) \end{bmatrix} \sigma_1(t_2). \end{aligned}$$

A natural question arises, when one can reconstruct $S(\lambda, t_2) \in \mathcal{I}$, when one knows its pole data, i.e., if one knows all pole triples for all z 's.

8.3 Realization theorem (of Mittag-Leffler type)

Let $S(\lambda, t_2) \in \mathcal{I}$. Suppose that in order to solve a Mittag Leffler type problem, we are given a pole triple for each t_2 , $(X(t_2), T, Y(t_2))$, where we have denoted the matrix T independent of t_2 . As we have seen, the pole pairs can be chosen so that the differential equations of lemma 8.2 with spectral matrix parameter T are satisfied. Then the following theorem answers the question of reconstructing $S(\lambda, t_2)$ from its pole triple.

Theorem 8.4 *Suppose that we are given a pole triple $(C(t_2), A, B(t_2)\sigma_1)$ for each t_2 with constant A and $C(t_2), B(t_2)\sigma_1$ solutions of the output (3.8) and the inverse input (5.3) ODEs with the matrix spectral parameter A . Suppose also that an analytic function $D(t_2)$ (the value at infinity) is given. Then the matrix function*

$$S(\lambda, t_2) = D(t_2) + C(t_2)(\lambda I - A)^{-1}B(t_2)\sigma_1 \quad (8.5)$$

maps solutions of (3.7) with spectral parameter λ to solutions of (3.8) with the same spectral parameter iff the linkage conditions (2.10.Link) are satisfied.

Proof: The proof is essentially the same as for theorem 8.1. In order to obtain that the function $S(\lambda, t_2)$ built in (8.5) maps solutions of (3.7) to solutions of (3.8) with the same spectral parameter, it is necessary to prove that $S(\lambda, t_2)$ satisfies the following differential equation:

$$\frac{\partial}{\partial t_2} S(\lambda, t_2) = \sigma_{1*}^{-1}(\sigma_{2*}\lambda + \gamma_*)S(\lambda, t_2) - S(\lambda, t_2)\sigma_1^{-1}(\sigma_2\lambda + \gamma), \quad (8.6)$$

i.e., is of the form defined by (3.9). Differentiating (8.5) we obtain

$$\begin{aligned} \frac{\partial}{\partial t_2} S(\lambda, t_2) &= \frac{\partial}{\partial t_2} D(t_2) + \sigma_{1*}^{-1}(\sigma_{2*}A + \gamma_*)C(t_2)(\lambda I - A)^{-1}B(t_2)\sigma_1 - \\ &\quad - C(t_2)(\lambda I - A)^{-1}B(t_2)(\sigma_2A + \gamma). \end{aligned}$$

This can be rewritten as

$$\begin{aligned} \frac{\partial}{\partial t_2} S(\lambda, t_2) &= \frac{\partial}{\partial t_2} D(t_2) - \sigma_{1*}^{-1}(t_2)\sigma_{2*}C(t_2)B(t_2)\sigma_1 + C(t_2)B(t_2)\sigma_2(t_2) + \sigma_{1*}^{-1}(t_2)\gamma_*(t_2)D(t_2) + \\ &\quad + \lambda(\sigma_{1*}^{-1}(t_2)\sigma_{2*}D(t_2) - D\sigma_1^{-1}\sigma_2) + \sigma_{1*}^{-1}(\sigma_{2*}\lambda + \gamma_*)(D(t_2) + C(t_2)(\lambda I - A)^{-1}B(t_2)\sigma_1(t_2)) - \\ &\quad - (D(t_2) + C(t_2)(\lambda I - A)^{-1}B(t_2))(\sigma_2\lambda + \gamma) = \\ &= \frac{\partial}{\partial t_2} D(t_2) - \sigma_{1*}^{-1}(t_2)\sigma_{2*}C(t_2)B(t_2)\sigma_1 + C(t_2)B(t_2)\sigma_2(t_2) + \sigma_{1*}^{-1}(t_2)\gamma_*(t_2)D(t_2) + \\ &\quad + \lambda(\sigma_{1*}^{-1}(t_2)\sigma_{2*}D(t_2) - D\sigma_1^{-1}\sigma_2) + \lambda(\sigma_{1*}^{-1}(t_2)\sigma_{2*}S(\lambda, t_2) - S(\lambda, t_2)\sigma_1^{-1}(\sigma_2\lambda + \gamma)). \end{aligned}$$

Demanding further that the differential equation (8.6) holds for $S(\lambda, t_2)$, we obtain, considering first big λ and then arbitrary one

1. $-\sigma_{1*}^{-1}\sigma_{2*}D(t_2) + D(t_2)\sigma_1^{-1}\sigma_2 = 0$ and
2. $\frac{\partial}{\partial t_2}D(t_2) - \sigma_{1*}^{-1}\gamma_*D(t_2) + D(t_2)\sigma_1^{-1}\gamma + \sigma_{1*}^{-1}\sigma_{2*}C(t_2)B(t_2)\sigma_1 - C(t_2)B(t_2)\sigma_2 = 0$.

Denoting $\tilde{D}(t_2) = \sigma_{1*}D(t_2)\sigma_1^{-1}$, we obtain that these conditions are

1. $-\sigma_{2*}D(t_2) + \tilde{D}(t_2)\sigma_2 = 0$ and
2. $\frac{\partial}{\partial t_2}D(t_2) - \sigma_{1*}^{-1}\gamma_*D(t_2) + \sigma_{1*}^{-1}\tilde{D}(t_2)\gamma + \sigma_{1*}^{-1}\sigma_{2*}C(t_2)B(t_2)\sigma_1 - C(t_2)B(t_2)\sigma_2 = 0$,

which are exactly the linkage conditions (2.10.Link). Thus the theorem holds. $\square$

References

- [ABP] D. Alpay, J. A. Ball, Y. Peretz, *System theory, operator models and scattering: the time-varying case*, J. Operator Theory 47(2002), pp. 245-286.
- [BC] J.A. Ball N.Cohen, *De Branges-Rovnyak operator models and systems theory: a survey*, Operator Theory: Advances and Applications, Vol. 50, Birkhauser-Verlag, Basel 1991.
- [BV] J.A. Ball and V. Vinnikov, *Overdetermined Multidimensional Systems: State Space and Frequency Domain Methods*, Mathematical Systems Theory, D. Gilliam and J. Rosenthal, eds., Inst. Math. and its Appl. Volume Series, Vol. 134, Springer-Verlag, New York (2003), 63–120
- [BGR] J. A. Ball, I. Gohberg, L. Rodman, *Interpolation of Rational Matrix Functions*, Operator theory: advances and applications, Birkhauser, 1990.
- [BGK] H. Bart, I. Gohberg, M.A. Kaashok, *Minimal factorization of matrix and operator functions*, OT1, Birkhauser-Verlag, Basel-Boston, 1979.
- [BFKD] H. Bart, I. Gohberg, M.A. Kaashok, P. Van Dooren. *Factorizations of transfer functions*, SIAM J. Control Optim., 18(6): 675–696, 1980.
- [CoLe] E.A Coddington, N. Levinson, *Theory of ordinary differential equation*, Mc-Graw Hill, 1955.
- [dBR] L. de Branges, J.R. Rovnyak, *Canonical models in quantum scattering theory*, in Pert. Theory and its Appl. in Quantum Mechanics, Wiley, New York, 1966, pp. 295-392.
- [B] M.S. Brodskii, *Triangular and Jordan representation of linear operators*, Moscow, Nauka, 1969 (Russian); English trans.: Amer. Math. Soc., Providence, 1974.
- [Ga] H. Gauchman, *Curvature colligations*. Integral Equations Operator Theory 7 (1984), no. 1, 45–59
- [H] J.W. Helton, Discrete time systems, operator models, and scattering theory, Journal of functional analysis 16, 15-38.
- [KFA] R.E. Kalman, P.L. Falb, M.A. Arbib, *Topics in mathematical system theory*, McGraw-Hill, 1969.

- [K] T. Kailath, *Linear Systems*, Prentice-Hall, New Jersey, 1980.
- [Li] M.S. Livšic, *Vortices of 2D systems*, Operator Theory: Advances and Applications, Vol. 123, Birkhauser-Verlag, Basel 2001.
- [LKMV] M.S. Livšic, N.Kravitsky, A.S. Markus and V. Vinnikov, *Theory of Commuting Nonselfadjoint Operators*, Kluwer Acad. Press, 1995.
- [La] C. Chicone, Y. Latushkin, *Evolution Semigroups in Dynamic Systems and Differential Equations*, Math. Surveys and Monographs, Vol. 70, Amer. Math. Soc. 1999.
- [NF] B. Sz.-Nagy, C. Foia's, *Harmonic analysis of operators on Hilbert space*, Translated from the French and revised, North-Holland, Amsterdam, 1970.
- [N] A. C. Newell, *Solitons in mathematics and physics*, Society for Industr. and Appl. Math., 1985.
- [P] V.P. Potapov, *On the multiplicative structure of J -nonexpanding matrix functions*, Trudy Moskov. Mat. Obschestva, 4 (1955), 125-236 (Russian); English transl.: Amer. Math. Soc. Transl. (2), 15 (1960), 131-243.
- [S] L. A. Sakhnovich, *Factorization of an operator transfer function* (Russian) Spectral theory of operators (Proc. Second All-Union Summer Math. School, Baku, 1975) (Russian), pp. 166–175, "Elm" Baku, 1979
- [V] V. Vinnikov, *Commuting operators and function theory on a Riemann surface*, Holomorphic spaces (Berkeley, CA, 1995), 445–476, Math. Sci. Res. Inst. Publ., 33, Cambridge Univ. Press, Cambridge, 1998.